



Compatibility Matrix for Legacy Cisco Wireless Solutions

First Published: 2023-02-20

Compatibility Matrix for Legacy Cisco Wireless Solutions

This document lists the software compatibility matrix information for the legacy Cisco wireless devices used in a Cisco centralized and distributed wireless LAN solution and in converged access solutions.

To view the currently supported Cisco wireless devices and the compatible Cisco software releases, see

<https://www.cisco.com/c/en/us/td/docs/wireless/compatibility/matrix/compatibility-matrix.html>

Conventions

See [Cisco Technical Tips Conventions](#) for information about document conventions.

Access Points and Cisco Wireless Software Releases Matrix

For information about access points that are currently supported, see

<https://www.cisco.com/c/en/us/td/docs/wireless/compatibility/matrix/compatibility-matrix.html>

For information about the features supported on Wave 2 and Wi-Fi 6 Access Points across Cisco IOS XE and AireOS platforms, see the [Feature Matrix for Wave 2 and 802.11ax \(Wi-Fi 6\) Access Points](#) document.

For information about compatibility of Cisco Prime Infrastructure with Cisco AireOS Wireless Controller, see [Cisco Prime Infrastructure Compatibility Matrix, on page 22](#).

For information about compatibility of Cisco Mobility Services Engine with Cisco AireOS Wireless Controller, see [Cisco Mobility Services Engine Compatibility Matrix, on page 143](#).

For compatibility information about Cisco AireOS Wireless Controller and Cisco ISE, see the [Cisco ISE Compatibility Information page](#).

Table 1: Cisco AireOS Wireless Controller Software Releases, AP IOS Releases, and Supported Access Points

Cisco Controller Release	Access Point IOS Release	Supported Access Points
7.6.130.0	15.2(4)JB6 12.4.25e-JAO6	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1270, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 600 OEAP, 700, 700W, AP801, and AP802
7.6.120.0	15.2(4)JB5 12.4(25e)JAO5	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1524S, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, and 1552D

Cisco Controller Release	Access Point IOS Release	Supported Access Points
7.6.110.0	15.2(4)JB4 12.4(25e)JAO4	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702j, 3702k, 3702l, 3702m, 3702n, 3702o, 3702p, 3702q, 3702r, 3702s, 3702t, 3702u, 3702v, 3702w, 3702x, 3702y, 3702z, 3702aa, 3702ab, 3702ac, 3702ad, 3702ae, 3702af, 3702ag, 3702ah, 3702ai, 3702aj, 3702ak, 3702al, 3702am, 3702an, 3702ao, 3702ap, 3702aq, 3702ar, 3702as, 3702at, 3702au, 3702av, 3702aw, 3702ax, 3702ay, 3702az, 3702ba, 3702bb, 3702bc, 3702bd, 3702be, 3702bf, 3702bg, 3702bh, 3702bi, 3702bj, 3702bk, 3702bl, 3702bm, 3702bn, 3702bo, 3702bp, 3702bq, 3702br, 3702bs, 3702bt, 3702bu, 3702bv, 3702bw, 3702bx, 3702by, 3702bz, 3702ca, 3702cb, 3702cc, 3702cd, 3702ce, 3702cf, 3702cg, 3702ch, 3702ci, 3702cj, 3702ck, 3702cl, 3702cm, 3702cn, 3702co, 3702cp, 3702cq, 3702cr, 3702cs, 3702ct, 3702cu, 3702cv, 3702cw, 3702cx, 3702cy, 3702cz, 3702da, 3702db, 3702dc, 3702dd, 3702de, 3702df, 3702dg, 3702dh, 3702di, 3702dj, 3702dk, 3702dl, 3702dm, 3702dn, 3702do, 3702dp, 3702dq, 3702dr, 3702ds, 3702dt, 3702du, 3702dv, 3702dw, 3702dx, 3702dy, 3702dz, 3702ea, 3702eb, 3702ec, 3702ed, 3702ee, 3702ef, 3702eg, 3702eh, 3702ei, 3702ej, 3702ek, 3702el, 3702em, 3702en, 3702eo, 3702ep, 3702eq, 3702er, 3702es, 3702et, 3702eu, 3702ev, 3702ew, 3702ex, 3702ey, 3702ez, 3702fa, 3702fb, 3702fc, 3702fd, 3702fe, 3702ff, 3702fg, 3702fh, 3702fi, 3702fj, 3702fk, 3702fl, 3702fm, 3702fn, 3702fo, 3702fp, 3702fq, 3702fr, 3702fs, 3702ft, 3702fu, 3702fv, 3702fw, 3702fx, 3702fy, 3702fz, 3702ga, 3702gb, 3702gc, 3702gd, 3702ge, 3702gf, 3702gg, 3702gh, 3702gi, 3702gj, 3702gk, 3702gl, 3702gm, 3702gn, 3702go, 3702gp, 3702gq, 3702gr, 3702gs, 3702gt, 3702gu, 3702gv, 3702gw, 3702gx, 3702gy, 3702gz, 3702ha, 3702hb, 3702hc, 3702hd, 3702he, 3702hf, 3702hg, 3702hh, 3702hi, 3702hj, 3702hk, 3702hl, 3702hm, 3702hn, 3702ho, 3702hp, 3702hq, 3702hr, 3702hs, 3702ht, 3702hu, 3702hv, 3702hw, 3702hx, 3702hy, 3702hz, 3702ia, 3702ib, 3702ic, 3702id, 3702ie, 3702if, 3702ig, 3702ih, 3702ii, 3702ij, 3702ik, 3702il, 3702im, 3702in, 3702io, 3702ip, 3702iq, 3702ir, 3702is, 3702it, 3702iu, 3702iv, 3702iw, 3702ix, 3702iy, 3702iz, 3702ja, 3702jb, 3702jc, 3702jd, 3702je, 3702jf, 3702jg, 3702jh, 3702ji, 3702jj, 3702jk, 3702jl, 3702jm, 3702jn, 3702jo, 3702jp, 3702jq, 3702jr, 3702js, 3702jt, 3702ju, 3702jv, 3702jw, 3702jx, 3702jy, 3702jz, 3702ka, 3702kb, 3702kc, 3702kd, 3702ke, 3702kf, 3702kg, 3702kh, 3702ki, 3702kj, 3702kk, 3702kl, 3702km, 3702kn, 3702ko, 3702kp, 3702kq, 3702kr, 3702ks, 3702kt, 3702ku, 3702kv, 3702kw, 3702kx, 3702ky, 3702kz, 3702la, 3702lb, 3702lc, 3702ld, 3702le, 3702lf, 3702lg, 3702lh, 3702li, 3702lj, 3702lk, 3702ll, 3702lm, 3702ln, 3702lo, 3702lp, 3702lq, 3702lr, 3702ls, 3702lt, 3702lu, 3702lv, 3702lw, 3702lx, 3702ly, 3702lz, 3702ma, 3702mb, 3702mc, 3702md, 3702me, 3702mf, 3702mg, 3702mh, 3702mi, 3702mj, 3702mk, 3702ml, 3702mm, 3702mn, 3702mo, 3702mp, 3702mq, 3702mr, 3702ms, 3702mt, 3702mu, 3702mv, 3702mw, 3702mx, 3702my, 3702mz, 3702na, 3702nb, 3702nc, 3702nd, 3702ne, 3702nf, 3702ng, 3702nh, 3702ni, 3702nj, 3702nk, 3702nl, 3702nm, 3702nn, 3702no, 3702np, 3702nq, 3702nr, 3702ns, 3702nt, 3702nu, 3702nv, 3702nw, 3702nx, 3702ny, 3702nz, 3702oa, 3702ob, 3702oc, 3702od, 3702oe, 3702of, 3702og, 3702oh, 3702oi, 3702oj, 3702ok, 3702ol, 3702om, 3702on, 3702oo, 3702op, 3702oq, 3702or, 3702os, 3702ot, 3702ou, 3702ov, 3702ow, 3702ox, 3702oy, 3702oz, 3702pa, 3702pb, 3702pc, 3702pd, 3702pe, 3702pf, 3702pg, 3702ph, 3702pi, 3702pj, 3702pk, 3702pl, 3702pm, 3702pn, 3702po, 3702pp, 3702pq, 3702pr, 3702ps, 3702pt, 3702pu, 3702pv, 3702pw, 3702px, 3702py, 3702pz, 3702qa, 3702qb, 3702qc, 3702qd, 3702qe, 3702qf, 3702qg, 3702qh, 3702qi, 3702qj, 3702qk, 3702ql, 3702qm, 3702qn, 3702qo, 3702qp, 3702qq, 3702qr, 3702qs, 3702qt, 3702qu, 3702qv, 3702qw, 3702qx, 3702qy, 3702qz, 3702ra, 3702rb, 3702rc, 3702rd, 3702re, 3702rf, 3702rg, 3702rh, 3702ri, 3702rj, 3702rk, 3702rl, 3702rm, 3702rn, 3702ro, 3702rp, 3702rq, 3702rr, 3702rs, 3702rt, 3702ru, 3702rv, 3702rw, 3702rx, 3702ry, 3702rz, 3702sa, 3702sb, 3702sc, 3702sd, 3702se, 3702sf, 3702sg, 3702sh, 3702si, 3702sj, 3702sk, 3702sl, 3702sm, 3702sn, 3702so, 3702sp, 3702sq, 3702sr, 3702ss, 3702st, 3702su, 3702sv, 3702sw, 3702sx, 3702sy, 3702sz, 3702ta, 3702tb, 3702tc, 3702td, 3702te, 3702tf, 3702tg, 3702th, 3702ti, 3702tj, 3702tk, 3702tl, 3702tm, 3702tn, 3702to, 3702tp, 3702tq, 3702tr, 3702ts, 3702tt, 3702tu, 3702tv, 3702tw, 3702tx, 3702ty, 3702tz, 3702ua, 3702ub, 3702uc, 3702ud, 3702ue, 3702uf, 3702ug, 3702uh, 3702ui, 3702uj, 3702uk, 3702ul, 3702um, 3702un, 3702uo, 3702up, 3702uq, 3702ur, 3702us, 3702ut, 3702uu, 3702uv, 3702uw, 3702ux, 3702uy, 3702uz, 3702va, 3702vb, 3702vc, 3702vd, 3702ve, 3702vf, 3702vg, 3702vh, 3702vi, 3702vj, 3702vk, 3702vl, 3702vm, 3702vn, 3702vo, 3702vp, 3702vq, 3702vr, 3702vs, 3702vt, 3702vu, 3702vv, 3702vw, 3702vx, 3702vy, 3702vz, 3702wa, 3702wb, 3702wc, 3702wd, 3702we, 3702wf, 3702wg, 3702wh, 3702wi, 3702wj, 3702wk, 3702wl, 3702wm, 3702wn, 3702wo, 3702wp, 3702wq, 3702wr, 3702ws, 3702wt, 3702wu, 3702wv, 3702ww, 3702wx, 3702wy, 3702wz, 3702xa, 3702xb, 3702xc, 3702xd, 3702xe, 3702xf, 3702xg, 3702xh, 3702xi, 3702xj, 3702xk, 3702xl, 3702xm, 3702xn, 3702xo, 3702xp, 3702xq, 3702xr, 3702xs, 3702xt, 3702xu, 3702xv, 3702xw, 3702xx, 3702xy, 3702xz, 3702ya, 3702yb, 3702yc, 3702yd, 3702ye, 3702yf, 3702yg, 3702yh, 3702yi, 3702yj, 3702yk, 3702yl, 3702ym, 3702yn, 3702yo, 3702yp, 3702yq, 3702yr, 3702ys, 3702yt, 3702yu, 3702yv, 3702yw, 3702yx, 3702yy, 3702yz, 3702za, 3702zb, 3702zc, 3702zd, 3702ze, 3702zf, 3702zg, 3702zh, 3702zi, 3702zj, 3702zk, 3702zl, 3702zm, 3702zn, 3702zo, 3702zp, 3702zq, 3702zr, 3702zs, 3702zt, 3702zu, 3702zv, 3702zw, 3702zx, 3702zy, 3702zz
7.6.100.0	15.2(4)JB3 12.4(25e)JAO3	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1532E, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.5.102.0	15.2(4)JA1 12.4(25e)JAN1	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 600 OEAP, 700, AP801, AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.4.150.0	15.2(2)JB6 12.4(25e)JAM6	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 3500e, 3500i, 3500p, 3600e, 3600i, 600 OEAP, AP801, AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552I, 1552C, 1552EU, 1552CU, and 1552S Note Initial support for –B regulatory domain APs.
7.4.140.0	15-2(2)JB5 12.4(25e)JAM5	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1600, 3500e, 3500i, 3500p, 3600e, 3600i, 600 OEAP, AP801, AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.4.130.0	15.2(2)JB3 12.4(25e)JAM4	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.4.121.0	15.2(2)JB3 12.4(25e)JAM3	
7.4.110.0	15.2(2)JB2 12.4(25e)JAM2	
7.4.100.60	15.2(2)JB1 12.4(25e)JAM1	
7.4.100.0	15.2(2)JB 12.4(25e)JAM	
7.3.112.0	15.2(2)JA1 12.4(25e)JAL2	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 2600, 3500i, 3600e, 3600i, 3500p, 600 OEAP, AP801, and AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552E, 1552I, 1552C, 1552EU, 1552CU, and 1552S
7.3.101.0	15.2(2)JA 12.4(25e)JAL	

Cisco Controller Release	Access Point IOS Release	Supported Access Points
7.2.115.2	12.4(25e)JA2	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 23500i, 3500p, 3600e, 3600i, 600 OEAP, AP801, and AP802
7.2.111.3	12.4(25e)JA2	Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552I, 1552C, and 1552S
7.2.110.0	12.4(25e)JA1	
7.2.103.0	12.4(25e)JA	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 3600e, 3500p, 3600i, 600 OEAP, AP801, and AP802 Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1552I, 1552C, and 1552S
7.0.252.0	12.4(23c)JA10	Lightweight APs: 1040, 1120, 1130, 1140, 1220, 1230, 1260, 1300, 3500, OEAP 600 Series, 3500p, AP801, and AP802 Outdoor and Industrial APs: 1522, 1524SB, 1552E, 1552C, and 1552S
7.0.251.2	12.4(23c)JA9	
7.0.250.0	12.4(23c)JA8	
7.0.240.0	12.4(23c)JA7	
7.0.235.3	12.4(23c)JA6	
7.0.235.0	12.4(23c)JA5	
7.0.230.0	12.4(23c)JA4	
7.0.220.0	12.4(23c)JA3	
7.0.116.0	12.4(23c)JA2	
7.0.98.218	12.4(23c)JZ	Lightweight APs: 1040, 1120, 1130, 1140, 1220, 1230, 1260, 1300, 3500, and AP801 Outdoor and Industrial APs: 1522, 1524PS, and 1524SB
7.0.98.0	12.4(23c)JA	
6.0.202.0	12.4(21a)JHC	Lightweight APs: 1120, 1130, 1140, 1230AG, 1240, 1250, and AP801 Outdoor and Industrial APs: 1522, 1524PS, and 1524SB
5.2.193.0	12.4(18a)JA2	Lightweight APs: 1120, 1130, 1140, 1220, 1230AG, 1240, and AP801 Outdoor and Industrial APs: 1522 and 1524PS
4.1.192.35M (Mesh Release 3)	—	1505, 1510, 1522, 1524PS, 1130, 1240
4.1.191.24M (Mesh Release 2)	—	1505, 1510, 1522 (US, Canada, and RoW), 1130, 1240

Cisco Controller Release	Access Point IOS Release	Supported Access Points
4.1.190.5 (Mesh Release 1)	—	1505, 1510, 1522 (US and Canada)

Software Release Support for Specific Access Point Modules

This section lists the Cisco AireOS Wireless Controller software releases that support specific Cisco access point modules. The First Support column lists the earliest Cisco AireOS Wireless Controller software release that supports the access point module. For access point modules that are not supported in ongoing releases, the Last Support column lists the last release that supports the access point module.

Table 2: Software Support for Access Point Modules

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
700W Series	AIR-CAP702Wx-K9	7.6.120.0	8.10.x	3.6.0E	Cisco IOS XE Release 3.6.xE
	AIR-CAP702W-xK910	7.6.120.0	8.10.x	3.6.0E	Cisco IOS XE Release 3.7.xE
700 Series	AIR-CAP702I-x-K9	7.5.102.0	8.10.x	3.6.0E	Cisco IOS XE 16.3.x
	AIR-CAP702W-x-K9	7.6.120.0	8.10.x	3.6.0E	
1000 Series	AIR-AP1010	3.0.100.0	4.2.209.0	—	—
	AIR-AP1020	3.0.100.0	4.2.209.0	—	—
	AIR-AP1030	3.0.100.0	4.2.209.0	—	—
	Airespace AS1200	—	4.0	—	—
	AIR-LAP1041N	7.0.98.0	8.3.x	3.2.0SE	Cisco IOS XE 16.3.x
	AIR-LAP1042N	7.0.98.0	8.3.x	3.2.0SE	Cisco IOS XE 16.3.x
1100 Series	AIR-LAP1121	4.0.155.0	7.0.x	—	—
	AIR-LAP1131	3.1.59.24	8.0.x	—	—
	AIR-LAP1141N	5.2.157.0	8.3.x	3.2.0SE	Cisco IOS XE 16.3.x
	AIR-LAP1142N	5.2.157.0	8.3.x	3.2.0SE	Cisco IOS XE 16.3.x
1220 Series	AIR-AP1220A	3.1.59.24	7.0.x	—	—
	AIR-AP1220B	3.1.59.24	7.0.x	—	—

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
1230 Series	AIR-AP1230A	3.1.59.24	7.0.x	—	—
	AIR-AP1230B	3.1.59.24	7.0.x	—	—
	AIR-LAP1231G	3.1.59.24	7.0.x	—	—
	AIR-LAP1232AG	3.1.59.24	7.0.x	—	—
1240 Series	AIR-LAP1242G	3.1.59.24	8.0.x	—	—
	AIR-LAP1242AG	3.1.59.24	8.0.x	—	—
1250 Series	AIR-LAP1250	4.2.61.0	8.0.x	—	—
	AIR-LAP1252G	4.2.61.0	8.0.x	—	—
	AIR-LAP1252AG	4.2.61.0	8.0.x	—	—
1260 Series	AIR-LAP1261N	7.0.116.0	8.3.x	3.2.0SE	Cisco IOS XE 16.3.x
	AIR-LAP1262N	7.0.98.0	8.3.x	3.2.0SE	Cisco IOS XE 16.3.x
1300 Series	AIR-BR1310G	4.0.155.0	7.0.x	—	—
1400 Series	Standalone Only	N/A	—	—	—
1600 Series	AIR-CAP1602I-x-K9	7.4.100.0	8.5.x	3.2.0SE	—
	AIR-CAP1602I-xK910	7.4.100.0	8.5.x	3.2.0SE	—
	AIR-SAP1602I-x-K9	7.4.100.0	8.5.x	3.2.0SE	Cisco IOS XE 16.3.x
	AIR-SAP1602I-xK9-5	7.4.100.0	8.5.x	3.2.0SE	
	AIR-CAP1602E-x-K9	7.4.100.0	8.5.x	3.2.0SE	
	AIR-SAP1602E-xK9-5	7.4.100.0	8.5.x	3.2.0SE	
1700 Series	AIR-CAP1702I-x-K9	8.0.100.0	8.10.x	3.7.0E	—
	AIR-CAP1702I-xK910		8.10.x		Cisco IOS XE Amsterdam 17.3.x
AP801	—	5.1.151.0	8.0.x	—	—
AP802	—	7.0.98.0	8.5.x	—	—
AP802H	—	7.3.101.0	8.5.x	—	—

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
AP803	—	8.1.122.0	8.10.x	—	—
ASA 5506W-AP702	—	8.1.122.0	8.10.x	—	—
2600 Series	AIR-CAP2602I-x-K9	7.2.110.0	8.5.x	3.2.0SE	Cisco IOS XE 16.3.x
	AIR-CAP2602I-xK910				
	AIR-SAP2602I-x-K9				
	AIR-SAP2602I-x-K95				
	AIR-CAP2602E-x-K9				
	AIR-CAP2602E-xK910				
2700 Series	AIR-CAP2702I-x-K9	7.6.120.0	8.10.x	3.6.0E	Cisco IOS XE Amsterdam 17.3.x
	AIR-CAP2702E-x-K9				
	AIR-AP2702I-U XK9	8.0.110.0		—	
3500 Series	AIR-CAP3501E	7.0.98.x	8.5.x	3.2.0SE	—
	AIR-CAP3501I				Cisco IOS XE 16.3.x
	AIR-CAP3502E				
	AIR-CAP3502I				
	AIR-CAP3502P	7.0.116.0			
3600 Series	AIR-CAP3602I	7.1.91.0	8.5.x	3.2.0SE	Cisco IOS XE 16.3.x
	AIR-CAP3602E				
3700 Series	AIR-CAP3702I	7.6.100.0	8.10.x	3.3.1SE	—
	AIR-CAP3702E				Cisco IOS XE Amsterdam 17.3.x
	AIR-CAP3702P				—
600 Series	AIR-OEAP602I	7.0.116.0	8.3.x	—	—
1500 Mesh Series	AIR-LAP-1505	3.1.59.24	4.2.207.54M	—	Cisco IOS XE 16.3.x
	AIR-LAP-1510	3.1.59.24	4.2.207.54M	—	

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
1520 Mesh Series	AIR-LAP1522AG	-A and N: 4.1.190.1 or 5.2 or later ¹ All other reg. domains: 4.1.191.24M or 5.2 or later 1	8.0.x	—	—
	AIR-LAP1522HZ	-A and N: 4.1.190.1 or 5.2 or later 1 All other reg. domains: 4.1.191.24M or 5.2 or later 1		—	—
	AIR-LAP1522PC	-A and N: 4.1.190.1 or 5.2 or later 1 All other reg. domains: 4.1.191.24M or 5.2 or later 1		—	—
	AIR-LAP1523CM	7.0.116.0 or later.		—	—
	AIR-LAP1524SB	-A, C and N: 6.0 or later All other reg. domains: 7.0.116.0 or later.		—	—
	AIR-LAP1524PS	-A: 4.1.192.22M or 5.2 or later 1		—	—

1	These access points are supported in the separate 4.1.19x.x mesh software release or with release 5.2 or later releases. These access points are not supported in the 4.2, 5.0, or 5.1 Releases.
2	The Cisco Aironet 1530 Series APs are supported operating only in Local mode; these APs in mesh mode are not supported.
3	The Cisco Aironet 1550 Series APs with 64-MB memory are not supported from Release 8.4.
4	y—Country DOCSIS Compliance, see ordering guide for details.

Related Information

- See the relevant release notes before you perform any software upgrade:
<https://www.cisco.com/c/en/us/support/wireless/wireless-lan-controller-software/products-release-notes-list.html>
- Product Approval Status: <https://cae-cnc-prd.cisco.com/ptcnc/>

- Wireless LAN Compliance Lookup:
<https://www.cisco.com/c/dam/assets/prod/wireless/wireless-compliance-tool/index.html>

Cisco AireOS Wireless Controller Platform and Software Releases

This section lists the Cisco AireOS Wireless Controller software releases in which the support started and ended, as applicable, for various Cisco AireOS Wireless Controller hardware platforms.

Table 3: Cisco AireOS Wireless Controller Platform Support in Software Releases

Cisco Controller Platform	First Support	Last Support
2100	4.2.x	7.x
2504	7.0.x	8.5
4400	4.2.x	7.x
5508	6.0.x	8.5
7510	7.0.x	8.5
WiSM	4.2.x	7.x
WiSM2 (1 DP)	7.0.x	8.5
WiSM2 (2 DP)	7.2.x	8.5
SRE	7.0.x	—

For information about supported hardware for Cisco Converged Access Solution, see [Converged Access Hardware Solution, on page 14](#).

IRCM Compatibility Matrix for AireOS Releases

Mobility, or roaming, is a wireless LAN client's ability to securely maintain its association seamlessly from one AP to another securely and with as little latency as possible. For more information about mobility in AireOS releases, see the *Information About Mobility* section in the [Controller Configuration Guide](#).

This section lists compatibility information between various AireOS releases, starting from 8.0.x, that involve Layer 2 and Layer 3 roaming and guest tunneling.

Table 4: IRCM Compatibility Matrix: 8.0.x to Later Releases

Release	80x	82x	83x	84x	85x	86x	87x	88x	89x	8.10x
8.0.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.2.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.3.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.4.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y

Release	80x	82x	83x	84x	85x	86x	87x	88x	89x	810x
8.5.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.6.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.7.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.8.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.9.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.10.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y

Cisco Mobility Express Solution Compatibility Matrix

This section contains compatibility information about the Cisco Mobility Express Solution.



Note The Cisco Mobility Express solution is not compatible with other Cisco Wireless Controller deployments and Cisco Network Assistant.

Table 5: Cisco Mobility Express Software Compatibility Matrix

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco Infr
8.10.162.0	15.3(3)JK6	APs with integrated controller functionality: Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, 3800 series, 4800 series, Cisco 6300 Series Embedded Services, and Cisco Catalyst IW6300 Heavy Duty Series APs without integrated controller functionality: Cisco Aironet 700i, 700w, 1700 series, 1810i, 1810w, 2700 series, 3700 series, Industrial Wireless 3702, Cisco Catalyst 9100	10.6.3-70	2.8	3.9
8.10.151.0	15.3(3)JK5		10.6.3-70	2.7	3.9
8.10.142.0	15.3(3)JK4		10.6.3-70		3.8
8.10.130.0	15.3(3)JK3		10.6.3-70	2.6	3.8
				2.4	3.8
				2.3	
				2.2	
				2.1	

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco P Infrastr
8.10.122.0 8.10.121.0 8.10.113.0 8.10.112.0 8.10.105.0	15.3(3)JK2a 15.3(3)JK2 15.3(3)JK1t 15.3(3)JK1 15.3(3)JK	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, 3800 series, 4800 series, Cisco 6300 Series Embedded Services, and Cisco Catalyst IW6300 Heavy Duty Series</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1700 series, 1810i, 1810w, 2700 series, 3700 series, Industrial Wireless 3702, Cisco Catalyst 9100</p>	10.6.3-70	2.6 2.4 2.3 2.2 2.1	3.7
8.9.111.0 8.9.100.0	15.3(3)JJ1 15.3(3)JJ	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, 3800 series, and 4800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1700 series, 1810i, 1810w, 2700 series, 3700 series, Industrial Wireless 3702, Cisco Catalyst 9100 (with Release 8.9.111.0)</p>	10.2.2 and later	2.6 2.4 2.3 2.2 2.1	3.7 3.6

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco Infr
8.8.130.0 8.8.125.0 8.8.120.0 8.8.111.0 8.8.100.0	15.3(3)JI6 15.3(3)JI5 15.3(3)JI4 15.3(3)JI3 15.3(3)JI1	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, 3800 series, and 4800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1700 series, 1810w, 2700 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.5 3.4 3.3 3.2 3.1. 3.1.
8.7.102.0	15.3(3)JH	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, and 3800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1700 series, 1810w, 2700 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.4 3.3 3.2 3.1. 3.1.
8.6.101.0	15.3(3)JG1	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, and 3800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1700 series, 1810w, 2700 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.4 3.3 3.2 3.1. 3.1.

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco P Infrastr
8.5.17x.0	15.3(3)JF14	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, and 3800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.9.1 3.9 3.8.1 3.8 3.7.1 3.7 3.6 3.5
8.5.16x.0	15.3(3)JF12i 15.3(3)JF12 15.3(3)JF11				
8.5.151.0	15.3(3)JF10				
8.5.140.0	15.3(3)JF9				
8.5.13x.0	15.3(3)JF8 15.3(3)JF7				
8.5.120.0	15.3(3)JF5				
8.5.110.0	15.3(3)JF4				
8.5.10x.0	15.3(3)JF1 15.3(3)JF				
8.4.100.0	15.3(3)JE				

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco Infr
8.3.130.0	15.3(3)JD7, 15.3(3)JDA7	<p>APs with integrated controller functionality:</p> <ul style="list-style-type: none"> • Cisco Aironet 1560, 1830, 1850, 2800, and 3800 series <p>APs without integrated controller functionality:</p> <ul style="list-style-type: none"> • Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series 	—	—	3.2 3.1.
8.3.122.0	15.3(3)JD6		—	—	3.1.
8.3.121.0	15.3(3)JD5				
8.3.112.0	15.3(3)JD4				
8.3.102.0	15.3(3)JD	<p>APs with integrated controller functionality:</p> <ul style="list-style-type: none"> • Cisco Aironet 1830, 1850, 2800, and 3800 series <p>APs without integrated controller functionality:</p> <ul style="list-style-type: none"> • Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series 	—	—	3.2 3.1. 3.1. 3.1.
8.2.100.0	15.3(3)JC	<p>APs with integrated controller functionality:</p> <ul style="list-style-type: none"> • Cisco Aironet 1850 series, 1830 series <p>APs without integrated controller functionality:</p> <ul style="list-style-type: none"> • Cisco Aironet 700i, 700w, 1600 series, 1700 series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series 	—	1.4	1.4 1.3
8.1.122.0	15.3(3)JBB5				1.3

Cisco Converged Access Solution

Converged Access Hardware Solution

Cisco 5760 Wireless Controller Models

Table 6: Cisco Controller 5700 Models

Part Number	Description
AIR-CT5760-25-K9	Cisco 5760 Wireless Controller for up to 25 Cisco access points
AIR-CT5760-50-K9	Cisco 5760 Wireless Controller for up to 50 Cisco access points
AIR-CT5760-100-K9	Cisco 5760 Wireless Controller for up to 100 Cisco access points
AIR-CT5760-250-K9	Cisco 5760 Wireless Controller for up to 250 Cisco access points
AIR-CT5760-500-K9	Cisco 5760 Wireless Controller for up to 500 Cisco access points
AIR-CT5760-1K-K9	Cisco 5760 Wireless Controller for up to 1000 Cisco access points
AIR-CT5760-HA-K9	Cisco 5760 Series Wireless Controller for High Availability

Cisco Aironet Series Universal Access Points

To see the list of supported Cisco Aironet Series Universal Access Points, see [Supported Cisco Aironet Series Universal Access Points](#) of the *Cisco Aironet Universal AP Priming and Cisco AirProvision User Guide*

Cisco Catalyst 3850 Switch Models

To see the list of supported Cisco Catalyst 3850 Switch models, see [Switch Models](#) of *Catalyst 3850 Switch Hardware Installation Guide*.

Cisco Catalyst 3650 Switch Models

To see the list of supported Cisco Catalyst 3650 Switch models, see [Switch Models](#) of *Catalyst 3650 Switch Hardware Installation Guide*.

Converged Access Solution Compatibility Matrix



- Note**
- Because of SHA-2 certificate implementation, Cisco MSE Release 7.6 is not compatible with Cisco IOS XE Release 3.6E. Therefore, we recommend that you upgrade to Cisco MSE Release 8.0.
 - IRCM Feature: Seamless roam between Cisco 5700 Controller, Catalyst 3850 and Cisco 5500 Controller, Cisco WiSM2 with Release 7.3.112.0 using New Mobility.
 - To see the list of supported Cisco AP models on the Cisco Catalyst [3650](#) and [3850](#) Series Switches, see the respective release notes.
 - Cisco MSE platforms running Cisco MSE Release 8.x are not compatible with the following Cisco switch platforms:
 - Cisco Catalyst 2960-24TT switch running Cisco Release 15.0(2)SE11
 - Cisco Catalyst 2960-48-PST-L switch running Cisco Release 15.0(2)SE11
 - Cisco Catalyst 2960X-24PS-L switch running Cisco Release 15.2(2)E7
 - Cisco Catalyst 3650-24PS switch running Cisco Release 16.3.5b
 - Cisco Catalyst 3560-24PS switch running Cisco Release 12.2(55)SE11
 - Cisco Catalyst 3850-24XS switch running Cisco Release 16.3.5.b
 - Cisco Nexus 5596UP switch running Cisco Release 7.1(4)N1(1)

Table 7: Converged Access Solution Compatibility Matrix

Catalyst 3850/3650 Switch	Cisco 5700 Series Controller	Cisco Controller Release	Cisco MSE	ISE	ACS
Cisco IOS XE Denali 16.3.3	03.07.05E	8.5	—	2.0 Patch 3	5.3
	03.07.04E	8.4		1.4 Patch 7	5.4
Cisco IOS XE Denali 16.3.2	03.07.03E	8.3		1.4 (Wireless)	5.5
Cisco IOS XE Denali 16.3.1	03.07.02E	8.2		1.3 Patch 6 (Wired and Wireless)	
	03.06.08E	8.1		1.3 Patch 5 (Wired and Wireless)	
Cisco IOS XE Denali 16.2.2	03.06.07E			1.3 Patch 3 (Wired)	
	03.06.06E				
Cisco IOS XE Denali 16.2.1	03.06.05aE				
	03.06.05E				
Cisco IOS XE Denali 16.1.1	03.06.04E				
	03.06.03E ¹				

Catalyst 3850/3650 Switch	Cisco 5700 Series Controller	Cisco Controller Release	Cisco MSE	ISE	ACS
03.07.05E	03.07.05E	8.1	8.0	1.3	5.2
03.07.04E	03.07.04E	8.0			5.3
03.07.03E	03.07.03E	7.6			
03.07.02E	03.07.02E				
03.07.01E	03.07.01E				
03.07.00E	03.07.00E				
03.06.10E	03.06.10E	8.0.x	8.0	2.4	5.2
03.06.09E	03.06.09E				
03.06.08E	03.06.08E	8.0	8.0	1.3	5.2
03.06.07E	03.06.07E	7.6		1.2	5.3
03.06.06E	03.06.06E				
03.06.05bE	03.06.05aE				
03.06.05E	03.06.05E				
03.06.04E	03.06.04E				
03.06.03E	03.06.03E				
03.06.02aE	03.06.02aE				
03.06.01E	03.06.01E				
03.06.00E	03.06.00E				
03.03.05SE	03.03.05SE	7.6 ⁴	7.6	1.2	5.2
03.03.04SE	03.03.04SE	7.5 ⁵	7.5		5.3
03.03.03SE	03.03.03SE				
03.03.02SE	03.03.02SE				
03.03.01SE	03.03.01SE				
03.03.00SE	03.03.00SE				

1	Cisco 5700 Series Controller (Cisco IOS XE Release 03.06.03E/ 03.07.02E) inter-operates as a Peer MC with Catalyst 3850 running on Cisco IOS XE 03.06.03E/ 03.07.02E releases.
2	Because of SHA-2 certificate implementation, Cisco MSE Release 7.6 is not compatible with Cisco IOS XE Release 3.6E and later. Therefore, we recommend that you upgrade to Cisco MSE Release 8.0.
3	If Cisco MSE is deployed on your network, we recommend that you upgrade to Cisco Prime Infrastructure 2.1.2.
4	Cisco Controller Release 7.6 is not compatible with Cisco Prime Infrastructure 2.0.

5	Prime Infrastructure 2.0 enables you to manage Cisco Controller 7.5.102.0 with the features of Cisco Controller 7.4.110.0 and earlier releases. Prime Infrastructure 2.0 does not support any features of Cisco Controller 7.5.102.0 including the new AP platforms.
---	--

Table 8: Converged Access Software Compatibility Matrix

Cisco 5700 Series Controller	Catalyst 3850 Switch	Catalyst 3650 Switch	Catalyst 4500E with Sup 8-E	Cisco Controller Release for Cisco 5508, WiSM2, or 2504¹ Controller Platforms	Cisco MSE
03.07.05E	03.07.05E	03.07.05E	03.09.01E	8.3.x	8.0
03.07.04E	03.07.04E	03.07.04E	03.09.00E	8.2.x	
03.07.03E	03.07.03E	03.07.03E	03.08.03E	8.1.x	
03.07.02E	03.07.02E	03.07.02E	03.08.02E	8.0	
03.07.01E	03.07.01E	03.07.01E	03.08.01E	7.6	
03.07.00E	03.07.00E	03.07.00E	03.08.00E		
03.06.09E	03.06.09E	03.06.09E	03.07.03E		
03.06.08E	03.06.08E	03.06.08E	03.07.02E		
03.06.07E	03.06.07E	03.06.07E	03.07.01E		
03.06.06E	03.06.06E	03.06.06E	03.07.00E		
03.06.05aE	03.06.05bE	03.06.05bE			
03.06.04E	03.06.04E	03.06.04E			
03.06.02aE	03.06.03E	03.06.03E			
03.06.01E	03.06.02aE	03.06.02aE			
03.06.00E	03.06.01E	03.06.01E			
	03.06.00E	03.06.00E			

Cisco 5700 Series Controller	Catalyst 3850 Switch	Catalyst 3650 Switch	Catalyst 4500E with Sup 8-E	Cisco Controller Release for Cisco 5508, WiSM2, or 2504 ¹ Controller Platforms	Cisco MSE
03.07.05E	03.07.05E	03.07.05E	03.07.03E	8.1.x	8.0
03.07.04E	03.07.04E	03.07.04E	03.07.02E	8.0	
03.07.03E	03.07.02E	03.07.03E	03.07.01E	7.6	
03.07.02E	03.07.01E	03.07.02E	03.07.00E		
03.07.01E	03.07.00E	03.07.01E			
03.07.00E	03.06.08E	03.07.00E			
03.06.08E	03.06.07E	03.06.08E			
03.06.07E	03.06.06E	03.06.07E			
03.06.06E	03.06.05aE	03.06.06E			
03.06.05aE	03.06.05E	03.06.05aE			
03.06.05E	03.06.04E	03.06.05E			
03.06.04E	03.06.02aE	03.06.04E			
03.06.02aE	03.06.01E	03.06.02aE			
03.06.01E	03.06.00E	03.06.01E			
03.06.00E		03.06.00E			
03.06.05aE	03.06.05bE	03.06.05bE	—	8.0	
03.06.05E	03.06.05E	03.06.05E		8.0.x	
03.06.04E	03.06.04E	03.06.04E		7.6.x	
03.06.02aE	03.06.03E	03.06.03E			
03.06.01E	03.06.02aE	03.06.02aE			
03.06.00E	03.06.01E	03.06.01E			
	03.06.00E	03.06.00E			
03.03.03SE	03.03.03SE	03.03.03SE	—	7.6 ⁴	7.6
03.03.02SE	03.03.02SE	03.03.02SE		7.5 ⁵	7.5
03.03.01SE	03.03.01SE	03.03.01SE			
03.03.00SE	03.03.00SE	03.03.00SE			
03.02.03SE	03.02.03SE	—	—	7.6.x	7.6
				7.5	7.5
				7.3.112.0	

Cisco 5700 Series Controller	Catalyst 3850 Switch	Catalyst 3650 Switch	Catalyst 4500E with Sup 8-E	Cisco Controller Release for Cisco 5508, WiSM2, or 2504 ¹ Controller Platforms	Cisco MSE
03.02.02SE	03.02.02SE	—	—	7.6.x 7.5 7.3.112.0	7.6 7.5
03.02.01SE	03.02.01SE	—	—	7.6.x 7.5 7.3.112.0	—
03.02.00SE	03.02.00SE	—	—	7.3.112.0	—

1	New Mobility is supported on Cisco 2504 Controller in 8.0.x and later releases.
2	Because of SHA-2 certificate implementation, Cisco MSE Release 7.6 is not compatible with Cisco IOS XE Release 3.6E and later. Therefore, we recommend that you upgrade to Cisco MSE Release 8.0.
3	If Cisco MSE is deployed on your network, we recommend that you upgrade to Cisco Prime Infrastructure 2.1.2.
4	Cisco Controller Release 7.6 is not compatible with Cisco Prime Infrastructure 2.0.
5	Prime Infrastructure 2.0 enables you to manage Cisco Controller 7.5.102.0 with the features of Cisco Controller 7.4.110.0 and earlier releases. Prime Infrastructure 2.0 does not support any features of Cisco Controller 7.5.102.0 including the new AP platforms.

Table 9: Cisco IOS XE to Cisco IOS Version Number Mapping

Cisco IOS XE Version	Cisco IOSd Version	Cisco Wireless Control Module Version	Access Point IOS Version
16.3.3	Not applicable	16.3.3.0	15.3(3)JPC3
16.3.2	Not applicable	16.3.2.0	15.3(3)JPC2
16.3.1	Not applicable	16.3.1.1	15.3(3)JPC1
16.3.0	Not applicable	16.3.1.0	15.3(3)JPC
16.2.1	Not applicable	16.2.2.0	15.3(3)JPB1
16.2.0	Not applicable	16.2.1.0	15.3(3)JPB
16.1.2	Not applicable	16.1.3.0	15.3(3)JNP2
16.1.1	Not applicable	16.1.2.0	15.3(3)JNP1

Cisco IOS XE Version	Cisco IOSd Version	Cisco Wireless Control Module Version	Access Point IOS Version
16.1.0	Not applicable	16.1.1.0	15.3(3)JNP
03.09.01E	15.2(5)E1	10.5.110.0	15.3(3)JND1
03.09.00E	15.2(5)E	10.5.100.0	15.3(3)JND
03.08.03E	15.2(4)E3	10.4.130.0	15.3(3)JNC3
03.08.02E	15.2(4)E2	10.4.120.0	15.3(3)JNC2
03.08.01E	15.2(4)E1	10.4.111.0	15.3(3)JNC1
03.08.00E	15.2(3)E	10.3.100.0	15.3(3)JNB
03.07.05E	15.2(3)E5	10.3.150.0	15.3(3)JNB6
03.07.04E	15.2(3)E4	10.3.141.0	15.3(3)JNB5
03.07.03E	15.2(3)E3	10.3.130.0	15.3(3)JNB3
03.07.02E	15.2(3)E2	10.3.120.0	15.3(3)JNB2
03.07.01E	15.2(3)E1	10.3.100.0	15.3(3)JNB1
03.06.10E	15.2(2)E10	10.2.200.0	15.3(3)JN17
03.06.09E	15.2(2)E9	10.2.190.0	15.3(3)JN15
03.06.08E	15.2(2)E8	10.2.180.0	15.3(3)JN14
03.06.07E	15.2(2)E7	10.2.170.0	15.3(3)JN12
03.06.06E	15.2(2)E6	10.2.160.0	15.3(3)JN11
03.06.05aE	15.2(2)E5	10.2.155.0	15.3(3)JN10
03.06.05E	15.2(2)E5	10.2.150.0	15.3(3)JN9
03.06.04E	15.2(2)E4	10.2.140.0	15.3(3)JN8
03.06.03E	15.2(2)E3	10.2.131.0	15.3(3)JN7
03.06.02E	15.2(2)E2	10.2.120.0	15.3(3)JN4
03.06.01E	15.2(2)E1	10.2.111.0	15.3(3)JN3
03.06.00E	15.2(2)E	10.2.102.0	15.3(3)JN
03.03.05SE	15.0(1)EZ5	10.1.150.0	15.2(4)JB7
03.03.04SE	15.0(1)EZ4	10.1.140.0	15.2(4)JB6
03.03.03SE	15.0(1)EZ3	10.1.130.0	15.2(4)JB5h

Cisco IOS XE Version	Cisco IOSd Version	Cisco Wireless Control Module Version	Access Point IOS Version
03.03.02SE	15.0(1)EZ2	10.1.121.0	15.2(4)JB3h
03.03.01SE	15.0(1)EZ1	10.1.110.0	15.2(4)JB2
03.03.00SE	15.0(1)EZ	10.1.100.0	15.2(4)JN
03.02.03SE	15.0(1)EX3	10.0.120.0	15.2(2)JN
03.02.02SE	15.0(1)EX2	10.0.111.0	15.2(2)JN
03.02.01SE	15.0(1)EX1	10.0.101.0	15.2(2)JN
03.02.00SE	15.0(1)EX	10.0.100.0	15.2(2)JN

CUWN Converged Access Solution Components and New (Hierarchical) Mobility IRCM Compatibility Matrix

New Mobility enables AireOS controllers to be compatible with converged access controllers with Wireless Control Module (WCM) such as the Cisco Catalyst 3850 Series Switches and the Cisco 5760 Wireless Controllers. New Mobility provides the ability to run Mobility Controller (MC) functionality on a controller in the Converged Access mode with a Catalyst 3850 mobility agent (MA). The Mobility Controller is a part of a hierarchical architecture that consists of a Mobility Agent and Mobility Oracle.

For more information about New Mobility, see the *Configuring New Mobility* chapter in the [Controller configuration guide](#).



Note New Mobility is not supported in Cisco Wireless Release 8.6 and later releases, Cisco IOS XE Release 3.10 and later releases, and Cisco IOS XE Release 16.4 and later releases.

Table 10: CUWN Converged Access Solution Components and New (Hierarchical) Mobility IRCM Compatibility Matrix

Service	7.3.112.0, 7.5 through 8.5	IOS XE 3.2.0SE through 3.10
Layer 2 and Layer 3 Roaming	Y	Y
Wireless Guest Anchor/Termination ¹	Y	Y
Cisco MSE Release 8.0 wIPS and AwIPS Rogue Detection ²	Y	Y
Fast Roaming (CCKM) in a mobility group	Y	Y
Location Services	Y	Y
Radio Resource Management (RRM) ³	Y	Y
Management Frame Protection (MFP)	Y	Y
AP Failover and SSO	Y	Y

1	Guest Anchor Termination is only supported on Cisco 2500 Series, 5700 Series, 5500 Series, 8500 Series, and Cisco WiSM2 platforms. The Cisco 2500 Series, 5700 Series, 5500 Series, 8500 Series, Cisco WiSM2, and Catalyst 3650 and 3850 are all supported as foreign controllers.
2	Rogue Detector Mode is not supported on Catalyst 3650 and 3850.
3	In Release 7.2, RF profiles and groups feature was introduced. RRM for Release 7.2 and later is not backward compatible with the earlier releases. RRM Converged Access is compatible with the controller software 7.6 and later releases but does not support RF Profiles and Groups feature that was introduced in Release 7.2.
4	AP SSO support for Cisco 5700 series controllers is supported in IOS XE 3.3.0SE release. AP Intra-OS Platform Fast Failover is supported. AP Inter-OS Platform Image Download and Reboot is performed.

Cisco Prime Infrastructure Compatibility Matrix

Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix

This section lists the Cisco Controller releases and Identity Services Engine (ISE) versions that are compatible with the Cisco Prime Infrastructure releases.

For information about wireless device support in Cisco Prime Infrastructure, see the following URL:

<https://www.cisco.com/c/en/us/support/cloud-systems-management/prime-infrastructure/products-device-support-tables-list.html>



Note

- For Cisco MSE compatibility details, see [Cisco Mobility Services Engine Compatibility Matrix](#).
- For Cisco MSE compatibility with Cisco Prime Infrastructure releases, see the applicable Cisco Prime Infrastructure release notes at: <https://www.cisco.com/c/en/us/support/cloud-systems-management/prime-infrastructure/products-release-notes-list.html>.

Table 11: Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.10.4		2.7	Cisco Prime Infrastructure release might not be supported for older controller versions < 8.5, however recommended to use Cisco Controller version 8.5 and above.
3.10.3		2.6	
3.10.2		2.4	
3.10.1		2.3	
3.10		2.2	
3.10		2.1	
3.9.1		2.0	
3.9		1.4	
3.8.1		1.3	
3.8			<p>Cisco Prime Infrastructure release might not be supported for older controller versions < 8.5, however recommended to use Cisco Controller version 8.5 and above.</p> <p>Cisco Prime Infrastructure release 3.8 does not support Catalyst 9800 Controller releases 16.12 and above.</p>

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.10.183.0		
	8.10.182.0		
	8.10.181.0		
	8.10.171.0		
	8.10.162.0		
	8.10.151.0		
	8.10.142.0		
	8.10.130.0		
	8.10.122.0		
	8.10.121.0		
	8.10.113.0		
	8.10.112.0		
	8.10.105.0		
	8.9.111.0		
	8.9.100.0		
	8.8.130.0		
	8.8.125.0		
	8.8.120.0		
	8.8.111.0		
	8.8.100.0		
	8.7.106.0		
	8.7.102.0		
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.5.110.0 8.5.105.0 8.5.103.0		
3.7.1	8.10.130.0 8.10.122.0 8.10.121.0 8.10.113.0 8.10.112.0 8.10.105.0 8.9.111.0 8.9.100.0 8.8.130.0 8.8.125.0 8.8.120.0 8.8.111.0 8.8.100.0 8.7.106.0 8.7.102.0 8.6.101.0 8.5.182.0 8.5.171.0 8.5.164.0 8.5.161.0 8.5.160.0 8.5.151.0 8.5.140.0 8.5.135.0 8.5.131.0 8.5.120.0 8.5.110.0 8.5.105.0 8.5.103.0	2.7 2.6 2.4 2.3 2.2 2.1 2.0 1.4 1.3	Cisco Prime Infrastructure release might not be compatible for older controller versions < 8.5, however, it is recommended to use Cisco Controller versions 8.5 and above.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.7	8.10.130.0	2.6	Cisco Prime Infrastructure release might include support for older controller versions < 8.5, however it is recommended to use Cisco Controller versions 8.5 and above.
	8.10.122.0	2.4	
	8.10.121.0	2.3	
	8.10.113.0	2.2	
	8.10.112.0	2.1	
	8.10.105.0	2.0	
	8.9.111.0	1.4	
	8.9.100.0	1.3	
	8.8.130.0		
	8.8.125.0		
	8.8.120.0		
	8.8.111.0		
	8.8.100.0		
	8.7.106.0		
	8.7.102.0		
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
	8.5.105.0		
8.5.103.0			

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.6	8.9.111.0	2.6	—
	8.9.100.0	2.4	
	8.8.130.0	2.3	
	8.8.125.0	2.2	
	8.8.120.0	2.1	
	8.8.111.0	2.0	
	8.8.100.0	1.4	
	8.7.106.0	1.3	
	8.7.102.0		
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
8.5.105.0			
8.5.103.0			

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.5	8.8.130.0	2.4	—
	8.8.125.0	2.3	
	8.8.120.0	2.2	
	8.8.111.0	2.1	
	8.8.100.0	2.0	
	8.7.106.0	1.4	
	8.7.102.0	1.3	
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
	8.5.105.0		
8.5.103.0			

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.4		2.4 2.3 2.2 2.1 2.0 1.4 1.3	—

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.7.106.0		
	8.7.102.0		
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
	8.5.105.0		
	8.5.103.0		
	8.4.100.0		
	8.3.150.0		
	8.3.143.0		
	8.3.141.0		
	8.3.140.0		
	8.3.133.0		
	8.3.132.0		
	8.3.130.0		
	8.3.12x.0		
	8.3.112.0		
	8.3.102.0		
	8.2.170.0		
	8.2.166.0		
	8.2.164.0		
	8.2.161.0		
	8.2.160.0		
	8.2.151.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.152.0		
	8.0.150.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.2.115.2 7.2.111.3 7.2.110.0 7.2.103.0 7.0.252.0 7.0.251.2 7.0.250.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.3		2.3 2.2 2.1 2.0 1.4 1.3	—

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.7.106.0		
	8.7.102.0		
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
	8.5.105.0		
	8.5.103.0		
	8.4.100.0		
	8.3.150.0		
	8.3.143.0		
	8.3.141.0		
	8.3.140.0		
	8.3.133.0		
	8.3.132.0		
	8.3.130.0		
	8.3.12x.0		
	8.3.112.0		
	8.3.102.0		
	8.2.170.0		
	8.2.166.0		
	8.2.164.0		
	8.2.161.0		
	8.2.160.0		
	8.2.151.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.152.0		
	8.0.150.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.2.115.2 7.2.111.3 7.2.110.0 7.2.103.0 7.0.252.0 7.0.251.2 7.0.250.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.2.1		2.2 2.1 2.0 1.4** 1.3**	**The latest Cisco Identity Services Engine Version works.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
	8.5.105.0		
	8.5.103.0		
	8.4.100.0		
	8.3.150.0		
	8.3.143.0		
	8.3.141.0		
	8.3.140.0		
	8.3.133.0		
	8.3.132.0		
	8.3.130.0		
	8.3.12x.0		
	8.3.112.0		
	8.3.102.0		
	8.2.170.0		
	8.2.166.0		
	8.2.164.0		
	8.2.161.0		
	8.2.160.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.152.0		
	8.0.150.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.2.103.0 7.0.252.0 7.0.251.2 7.0.250.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.2		2.2 2.1 2.0 1.4** 1.3**	**The latest Cisco Identity Services Engine Version works.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
	8.5.105.0		
	8.5.103.0		
	8.4.100.0		
	8.3.150.0		
	8.3.143.0		
	8.3.141.0		
	8.3.140.0		
	8.3.133.0		
	8.3.132.0		
	8.3.130.0		
	8.3.12x.0		
	8.3.112.0		
	8.3.102.0		
	8.2.170.0		
	8.2.166.0		
	8.2.164.0		
	8.2.161.0		
	8.2.160.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.152.0		
	8.0.150.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.2.103.0 7.0.252.0 7.0.251.2 7.0.250.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.1.7		2.2 2.1 2.0 1.4** 1.3**	**The latest Cisco Identity Services Engine Version works.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.4.100.0		
	8.3.150.0		
	8.3.143.0		
	8.3.141.0		
	8.3.140.0		
	8.3.133.0		
	8.3.132.0		
	8.3.130.0		
	8.3.12x.0		
	8.3.111.0		
	8.3.112.0		
	8.3.102.0		
	8.2.170.0		
	8.2.166.0		
	8.2.164.0		
	8.2.161.0		
	8.2.160.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.152.0		
	8.0.150.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.1.6		2.2 2.1 2.0 1.4** 1.3**	**The latest Cisco Identity Services Engine (ISE) Version works.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.4.100.0		
	8.3.150.0		
	8.3.143.0		
	8.3.141.0		
	8.3.140.0		
	8.3.133.0		
	8.3.132.0		
	8.3.130.0		
	8.3.12x.0		
	8.3.112.0		
	8.3.111.0		
	8.3.102.0		
	8.2.170.0		
	8.2.166.0		
	8.2.164.0		
	8.2.161.0		
	8.2.160.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.152.0		
	8.0.150.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.1.5		2.1 2.0 1.4** 1.3**	**The latest Cisco Identity Services Engine Version works.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.4.100.0		
	8.3.150.0		
	8.3.143.0		
	8.3.141.0		
	8.3.140.0		
	8.3.133.0		
	8.3.132.0		
	8.3.130.0		
	8.3.12x.0		
	8.3.112.0		
	8.3.102.0		
	8.2.170.0		
	8.2.166.0		
	8.2.164.0		
	8.2.161.0		
	8.2.160.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.152.0		
	8.0.150.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.1.4		2.1 2.0 1.4** 1.3	**For Cisco Prime Infrastructure 3.1.4 to work, apply Cisco Identity Services Engine (ISE) Patch (1.4.0.253-Patch3-141133) to an existing ISE 1 installation.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.3.150.0		
	8.3.143.0		
	8.3.141.0		
	8.3.140.0		
	8.3.133.0		
	8.3.132.0		
	8.3.130.0		
	8.3.12x.0		
	8.3.112.0		
	8.3.102.0		
	8.2.170.0		
	8.2.166.0		
	8.2.164.0		
	8.2.161.0		
	8.2.160.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.152.0		
	8.0.150.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.1.3		2.0 1.4** 1.3	*Cisco Aironet 1810 Series OEAPs are not supported. **For Cisco Prime Infrastructure 3.1.3 to work with ISE 1.4, you must apply Cisco Identity Services Engine (ISE) 1.4.0.253-Patch3-141133 to an existing ISE installation.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.3.150.0		
	8.3.143.0		
	8.3.141.0		
	8.3.140.0		
	8.3.133.0		
	8.3.132.0		
	8.3.130.0		
	8.3.12x.0		
	8.3.112.0		
	8.3.102.0		
	8.2.170.0		
	8.2.166.0		
	8.2.164.0		
	8.2.161.0		
	8.2.160.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.152.0		
	8.0.150.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.1.1		2.0 1.4** 1.3	<p>**For Cisco Prime Infrastructure 3.1.1 to work, apply Cisco Identity Services Engine (ISE) Patch (1.4.0.253-Patch3-141133) to an existing ISE 1 installation.</p> <p>***No new features of Cisco Controller 8.3.x are supported with Cisco Prime Infrastructure Release 3.1.1.</p>

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.3.13x.0		
	8.3.12x.0		
	8.3.112.0***		
	8.3.102.0***		
	8.2.170.0		
	8.2.16x.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.1		2.0 1.4** 1.3	**For Cisco Prime Infrastructure 3.1 to work with Cisco AireOS Controller 7.2.3, you must apply Cisco Identity Services Engine (ISE) 1.4.0.253-Patch3-141133 to an existing ISE installation.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.2.170.0		
	8.2.16x.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.0 Technology Package		1.4** 1.3	**For Cisco Prime Infrastructure 3.0 to work, you must apply Cisco Identity Services Engine (ISE) Patch 3 (1.4.0.253-Patch3-141133) to an existing ISE 1.3 installation.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.2.16x.0		
	8.2.151.0		
	8.2.141.0		
	8.2.130.0		
	8.2.121.0		
	8.2.111.0		
	8.2.110.0		
	8.2.100.0		
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.3.101.0 7.2.115.2 7.2.111.3 7.2.110.0 7.2.103.0 7.0.252.0 7.0.251.2 7.0.250.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.0.3		1.4** 1.3	*No new features of Cisco Controller 8.1.13 supported with Cisco Prime Infrastructure R the Mobility Express features are supported **For Cisco Prime Infrastructure 3.0 to work apply Cisco Identity Services Engine (ISE) (1.4.0.253-Patch3-141133) to an existing IS installation.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.1.131.0*		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.0.2		1.4** 1.3	*No new features of Cisco Controller 8.1.131.0 supported with Cisco Prime Infrastructure Release 3.0.2. The Mobility Express features are supported. **For Cisco Prime Infrastructure 3.0 to work, you must apply Cisco Identity Services Engine (ISE) Patch 1.4.0.253-Patch3-141133 to an existing ISE 1.4.0.253 installation.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.1.131.0*		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.0.1		1.4** 1.3	*No new features of Cisco Controller 8.1.13 supported with Cisco Prime Infrastructure R the Mobility Express features are supported **For Cisco Prime Infrastructure 3.0 to work apply Cisco Identity Services Engine (ISE) (1.4.0.253-Patch3-141133) to an existing IS installation.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.1.131.0*		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
3.0		1.4** 1.3	*No new features of Cisco Controller 8.1.122.0 including Mobility Express is supported with PI 3.0. **For PI 3.0 to work, you must apply Cisco Identity Engine (ISE) Patch 3 Version (1.4.0.253-Patch3) to an existing ISE 1.4.0 installation.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.1.131.0		
	8.1.122.0*		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
2.2.3		1.4** ¹ 1.3	<p>**For PI 2.2.3 to work, you must apply Cisco Services Engine (ISE) Patch 3 Version (1.4.0.253-Patch3-141133) to an existing ISE installation.</p> <p>Cisco Prime Infrastructure 2.2.2 allows you to use Cisco AireOS Controller 8.1.x; however, features introduced in Cisco AireOS Controller 8.1.x are not supported.</p>

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
2.2.2		1.3	Cisco Prime Infrastructure 2.2.2 allows you to manage Cisco AireOS Controller 8.1.x; however, features introduced in Cisco AireOS Controller 8.1.x are not supported.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
2.2.1		1.3	Cisco Prime Infrastructure 2.2.1 allows you to connect to Cisco AireOS Controller 8.1.x; however, features introduced in Cisco Prime Infrastructure 2.2.1 and Cisco AireOS Controller 8.1.x are not supported.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.1.131.0		
	8.1.122.0		
	8.1.111.0		
	8.1.102.0		
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
2.2		1.3 1.2*** 1.1 1.0	<p>* Prime Infrastructure 2.2 allows you to manage Cisco AireOS Controller Release 8.0.110.0.</p> <p>** Prime Infrastructure 2.2 allows you to manage Cisco AireOS MSE Release 8.0.110.0. For more information on supported MSE model and platform details, see Table 17: Compatibility Matrix for Software Versions 7.5.1 through 8.x, on page 146</p> <p>*** Prime Infrastructure supports ISE 1.2 in non-standalone mode.</p> <p>Note For version compatibility for Cisco Prime Infrastructure Release 8.0 w/IPS with PI 2.2, the Cisco Prime Infrastructure Release Notes.</p>

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.0.15x.0		
	8.0.140.0		
	8.0.13x.0		
	8.0.121.0		
	8.0.120.0		
	8.0.115.0		
	8.0.110.0		
	8.0.100.0		
	7.6.130.0		
	7.6.120.0		
	7.6.110.0		
	7.6.100.0		
	7.5.102.0		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
2.1.2***		1.0 1.1 1.2	<p>* Prime Infrastructure 2.1.2 allows you to manage Cisco Controller Releases 7.5.102.0, 7.6.x, and 8.0.x. Prime Infrastructure 2.1.2 does not support features of Cisco Controller 7.4.130.0 and earlier releases. Prime Infrastructure 2.1.2 does not support features that are introduced in Cisco Controller Releases 7.5.102.0 and 7.6.x except the new access point support feature and the new mobility feature.</p> <p>** Prime Infrastructure 2.1.2 allows you to manage Cisco MSE Releases 7.5.102.101, 7.6.100.0, 7.6.120.0, and 8.0.110.0 with feature compatibility of Cisco Prime Infrastructure Release 7.4.121.0. Prime Infrastructure 2.1.2 does not support any new features introduced in Cisco Controller Releases 7.5.102.101 and 7.6.120.0.</p> <p>*** Cisco AP701E is not supported by Prime Infrastructure 2.1.2.</p>

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.0.15x.0		
	8.0.140.0*		
	8.0.13x.0*		
	8.0.121.0*		
	8.0.120.0*		
	8.0.115.0*		
	8.0.110.0*		
	8.0.100.0*		
	7.6.130.0*		
	7.6.120.0*		
	7.6.110.0*		
	7.6.100.0*		
	7.5.102.0*		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
2.1.1***		1.0 1.1 1.2	<p>* Prime Infrastructure 2.1.1 allows you to manage Cisco AireOS Controller Releases 7.5.102.0, 7.6.100.0, 7.6.110.0, 7.6.120.0, and 8.0.100.0 with the features of Cisco Prime Infrastructure 2.1.1. Cisco Prime Infrastructure 2.1.1 does not support any features that are introduced in Cisco AireOS Controller Releases 7.5.102.0 and 7.6.x e... new access point platforms and the new mobility services.</p> <p>** Prime Infrastructure 2.1.1 allows you to manage Cisco MSE Releases 7.5.102.101, 7.6.100.0, 7.6.120.0, and 8.0.110.0 with feature compatibility of Cisco Prime Infrastructure Release 7.4.121.0. Prime Infrastructure 2.1.1 does not support any new features introduced in Cisco MSE Releases 7.5.102.101 and 7.6.120.0. For information on supported model and platform details, see Cisco Prime Infrastructure 2.1.1 Release Notes.</p> <p>*** Cisco AP701E is not supported by Prime Infrastructure 2.1.1. Also, Cisco Aironet 1700 Series Access Points are not supported by Prime Infrastructure until Prime Infrastructure Release 2.2.</p>

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	8.0.15x.0		
	8.0.140.0*		
	8.0.13x.0*		
	8.0.121.0*		
	8.0.120.0*		
	8.0.115.0*		
	8.0.110.0*		
	8.0.100.0*		
	7.6.130.0*		
	7.6.120.0*		
	7.6.110.0*		
	7.6.100.0*		
	7.5.102.0*		
	7.4.150.0		
	7.4.140.0		
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
	7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0		
2.1	7.6.120.0* 7.5.102.0* 7.4.150.0 7.4.140.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.115.2 7.2.111.3 7.2.110.0 7.2.103.0 7.0.252.0 7.0.251.2 7.0.250.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	1.0 1.1 1.2	<p>*Prime Infrastructure 2.1 allows you to manage Cisco Controller Releases 7.5.102.0 and 7.6.120.0 with the compatibility of Cisco Controller 7.4.130.0 and earlier releases. Prime Infrastructure 2.1 does not support any features introduced in Cisco Controller Releases 7.5.102.0 and later, except the new access point platforms and the new feature.</p> <p>** Prime Infrastructure 2.1 allows you to manage Cisco MSE Releases 7.5.102.101 and 7.6.120.0 with the compatibility of Cisco MSE Release 7.4.121.0. Prime Infrastructure 2.1 does not support any new features introduced in Cisco MSE Releases 7.5.102.101 and later, except 7.6.120.0.</p>

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
2.0	7.5.102.0* 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.115.2 7.2.111.3 7.2.110.0 7.2.103.0 7.0.252.0 7.0.251.2 7.0.250.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	1.0 1.1 1.2	<p>* Cisco Prime Infrastructure 2.0 enables you to upgrade from Cisco Controller 7.5.102.0 with the features introduced in Cisco Controller 7.4.130.0 and earlier releases. Prime Infrastructure 2.0 does not support any features introduced in Cisco Controller 7.5.102.0 or later releases, including the new access point platforms.</p> <p>** Cisco Prime Infrastructure 2.0 enables you to upgrade from Cisco MSE v7.5.102.101 or later releases of Cisco MSE v7.5.102.101 or later releases of Cisco MSE v7.5.102.101 or later releases of Cisco MSE Release 7.4.121.0 and earlier releases. Prime Infrastructure 2.0 does not support any features introduced in Cisco MSE Release 7.5.102.101 or later releases.</p>

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
Update 2 for 1.4.0.45	7.5.102.0	1.0	The Update 2 for Cisco Prime Infrastructure 1.4.0.45 allows you to manage Cisco Controller 7.6.x with the 1.4.0.45 Cisco Controller 7.5.102.0 and earlier releases. This release does not support any new features of Cisco Controller 7.6.x. However, this release supports two new AP platforms—Cisco 702w and Cisco 2700.
	7.4.150.0	1.1	
	7.4.140.0	1.2	
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
7.0.98.0			

Note For version compatibility for Cisco Prime Infrastructure Release 8.0 wIPS with Update 2 for Cisco Prime Infrastructure 1.4.0.45, see the Cisco Prime Infrastructure 8.0 wIPS Release Notes.

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
Update 1 for 1.4.0.45	7.5.102.0	1.0	<p>The Update 1 for Cisco Prime Infrastructure 1.4.0.45 allows you to manage Cisco Controller 7.6.x with the Cisco Controller 7.5.102.0 and earlier releases. However, the Aironet 3700 Series Access Points are not supported.</p> <p>Note For version compatibility for Cisco Prime Infrastructure Release 8.0 wIPS with Update 1 for 1.4.0.45, see Table 17: Cisco MSE Compatibility for Software Versions 7.5.x through 7.6.x on page 146.</p>
	7.4.150.0	1.1	
	7.4.140.0	1.2	
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
1.4.0.45	7.5.102.0	1.0	—
	7.4.150.0	1.1	
	7.4.140.0	1.2	
	7.4.130.0		
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
Update 4 for 1.3.0.20	7.4.150.0	1.0	—
Update 1 for 1.3.0.20	7.4.140.0	1.1	
1.3.0.20	7.4.130.0	1.2	
	7.4.121.0		
	7.4.110.0		
	7.4.100.60		
	7.4.100.0		
	7.3.112.0		
	7.3.101.0		
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		

Cisco Prime Infrastructure	Cisco AireOS Controller	ISE	Remarks
1.2.1.12	7.3.112.0	1.0	—
	7.3.101.0	1.1	
	7.2.115.2		
	7.2.111.3		
	7.2.110.0		
	7.2.103.0		
	7.0.252.0		
	7.0.251.2		
	7.0.250.0		
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.1.91.0		
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		

1	Cisco ISE Release 2.x or 1.4 only works with Cisco MSE Release 8.0 or earlier.
---	--

Cisco Prime Infrastructure, Cisco Catalyst 9800 Series Wireless Controllers and Cisco Converged Access Solution Compatibility Matrix

[Cisco Prime Infrastructure, Cisco Catalyst 9800 Series Wireless Controllers and Cisco Converged Access Solution Compatibility Matrix, on page 104](#) lists the Cisco IOS/IOS XE releases and the corresponding devices that are compatible with the Cisco Prime Infrastructure releases.

Table 12: Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release		Device	Remarks
3.10.4	Current Release with N-2 supported	Dublin 17.11.1	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure 3.10.2, 3.10.1, 3.10, 3.9.1 and 3.9 support Cisco IOS/IOS XE Amsterdam-17.3.5a For instructions to enable backward compatibility, see the Enable Backward Compatibility section in the latest <i>Cisco Prime Infrastructure</i> release. Note: Cisco Prime Infrastructure 3.10.2, 3.10.1, 3.10, 3.9.1 and 3.9 do not support Cisco IOS/IOS XE Amsterdam-17.3.5a.
		Dublin 17.10.1	Cisco Catalyst 9800-80 Wireless Controller	
		Cupertino 17.9.3	Cisco Catalyst 9800-L-F Wireless Controller	
		Cupertino 17.9.2	Cisco Catalyst 9800-CL Wireless Controller for Cloud	
		Cupertino 17.9.1		
		Cupertino 17.8.1		
		Cupertino 17.7.1		
	Bengaluru 17.6.4			
3.10.3	Current Release with N-2 supported	Dublin 17.10.1	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure 3.10.1, 3.10, 3.9.1 and 3.9 support Cisco IOS/IOS XE Amsterdam-17.3.5a For instructions to enable backward compatibility, see the Enable Backward Compatibility section in the latest <i>Cisco Prime Infrastructure</i> release. Note: Cisco Prime Infrastructure 3.10.1, 3.10, 3.9.1 and 3.9 do not support Cisco IOS/IOS XE Amsterdam-17.3.5a.
		Cupertino 17.9.3	Cisco Catalyst 9800-80 Wireless Controller	
		Cupertino 17.9.2	Cisco Catalyst 9800-L-F Wireless Controller	
		Cupertino 17.9.1	Cisco Catalyst 9800-CL Wireless Controller for Cloud	
		Cupertino 17.8.1		
		Cupertino 17.7.1		
	Bengaluru 17.6.4			
3.10.2	Current Release with N-2 supported	Cupertino 17.9.1	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure 3.9.1 and 3.9 support Cisco IOS/IOS XE Amsterdam-17.3.5a For instructions to enable backward compatibility, see the Enable Backward Compatibility section in the latest <i>Cisco Prime Infrastructure</i> release. Note: Cisco Prime Infrastructure 3.9.1 and 3.9 do not support Cisco IOS/IOS XE Amsterdam-17.3.5a.
		Cupertino 17.8.1	Cisco Catalyst 9800-80 Wireless Controller	
		Cupertino 17.7.1	Cisco Catalyst 9800-L-F Wireless Controller	
			Cisco Catalyst 9800-CL Wireless Controller for Cloud	
3.10.1	Current Release with N-2 supported	Cupertino 17.8.1	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure 3.10.2, 3.10.1, 3.10, 3.9.1 and 3.9 support Cisco IOS/IOS XE Amsterdam-17.3.5a For instructions to enable backward compatibility, see the Enable Backward Compatibility section in the latest <i>Cisco Prime Infrastructure</i> release. Note: Cisco Prime Infrastructure 3.10.2, 3.10.1, 3.10, 3.9.1 and 3.9 do not support Cisco IOS/IOS XE Amsterdam-17.3.5a.
		Cupertino 17.7.1	Cisco Catalyst 9800-80 Wireless Controller	
		Bengaluru 17.6.3	Cisco Catalyst 9800-L-F Wireless Controller	
		Bengaluru 17.6.4	Cisco Catalyst 9800-CL Wireless Controller for Cloud	
		Amsterdam 17.3.5a		

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release		Device	Remarks
3.10	Current Release with N-2 supported	Bengaluru 17.6.x	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure Release 16.10 support Cisco IOS XE Gibraltar 16.11 and 16.10. For instructions to enable support for Cisco IOS XE Gibraltar, see the Enable Backward Compatibility section in the latest <i>Cisco Prime Infrastructure</i> release. Note: Cisco Prime Infrastructure Release 16.10 do not support Cisco IOS/IOS XE Release 16.10.
		Bengaluru 17.5.1	Cisco Catalyst 9800-80 Wireless Controller	
		Bengaluru 17.4.1		
3.9.1	Current Release with N-2 supported	Bengaluru 17.5.1	Cisco Catalyst 9800-L-F Wireless Controller	Note: Cisco Prime Infrastructure Release 16.10 do not support Cisco IOS/IOS XE Release 16.10.
		Bengaluru 17.4.1	Cisco Catalyst 9800-CL Wireless Controller for Cloud	
3.9	Current Release with N-2 supported	Amsterdam 17.3.x		
		Bengaluru 17.4.1		
		Amsterdam 17.3.x		
		Amsterdam 17.2		
3.8.1	Current Release with N-2 supported	Amsterdam 17.3.x	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure Release 16.10 support Cisco IOS/IOS XE Release 16.10.
		Amsterdam 17.2	Cisco Catalyst 9800-80 Wireless Controller	
		Amsterdam 17.1	Cisco Catalyst 9800-L-F Wireless Controller	
			Cisco Catalyst 9800-CL Wireless Controller for Cloud	
3.8	Current Release with N-2 supported	Amsterdam 17.2.1	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure Release 16.11 and 16.10 support Cisco IOS/IOS XE Release 16.11 and 16.10.
		Amsterdam 17.1	Cisco Catalyst 9800-80 Wireless Controller	
			Cisco Catalyst 9800-L-F Wireless Controller	
			Cisco Catalyst 9800-CL Wireless Controller for Cloud	
3.7.1	Current Release with N-2 supported	Amsterdam 17.1	Cisco Catalyst 9800-40 Wireless Controller	—
		Gibraltar 16.12.x	Cisco Catalyst 9800-80 Wireless Controller	
		Gibraltar 16.11	Cisco Catalyst 9800-L-F Wireless Controller	
			Cisco Catalyst 9800-CL Wireless Controller for Cloud.	

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release		Device	Remarks
3.7	Current Release	Gibraltar 16.12.x Gibraltar 16.11 Gibraltar 16.10	Cisco Catalyst 9800-40 Wireless Controller Cisco Catalyst 9800-80 Wireless Controller Cisco Catalyst 9800-L-F Wireless Controller Cisco Catalyst 9800-CL Wireless Controller for Cloud.	—
3.6	Current Release	Gibraltar 16.10 Gibraltar 16.11 Gibraltar 16.9	Cisco Catalyst 9800-CL Wireless Controller for Cloud Cisco Catalyst 9800-40 Wireless Controller	—
3.5	Current Release	Gibraltar 16.9 Gibraltar 16.10 Denali 16.3.3 Denali 16.3.2 Denali 16.3.1	Cisco Catalyst 9800-CL Wireless Controller for Cloud Cisco Catalyst 9800-40 Wireless Controller	—

Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix

Table 13: Cisco PI and Cisco IOS/IOS-XE Releases

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.4	Denali 16.3.3	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch	Denali 16.x.x does not support Release 8.0.x.
	Denali 16.3.2		
	Denali 16.3.1	Cisco Catalyst 3650 Switch / Catalyst 36xx stackable Ethernet Switch	
	Denali 16.2.2		
	Denali 16.1.2	Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	
	Denali 16.2.1		
	Denali 16.1.1	Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	
	03.07.03E		
	03.07.002E		
	03.07.001E		
	03.07.000E		
	03.06.03E		
	03.06.02E		
	03.06.01E		
03.06.00E			
3.3	Denali 16.3.3	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch	Denali 16.x.x does not support Release 8.0.x.
	Denali 16.3.2		
	Denali 16.3.1	Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch	
	Denali 16.2.2		
	Denali 16.1.2	Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	
	Denali 16.2.1		
	Denali 16.1.1	Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	
	03.07.03E		
	03.07.002E		
	03.07.001E		
	03.07.000E		
	03.06.03E		
	03.06.02E		
	03.06.01E		
03.06.0			

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.2	Denali 16.3.3 Denali 16.3.2 Denali 16.3.1 Denali 16.2.2 Denali 16.1.2 Denali 16.2.1 Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support Release 8.0.x.
3.1.7	Denali 16.3.3 Denali 16.3.2 Denali 16.3.1 Denali 16.2.2 Denali 16.1.2 Denali 16.2.1 Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support Release 8.0.x.

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.1.6	Denali 16.3.3 Denali 16.3.2 Denali 16.3.1 Denali 16.2.2 Denali 16.1.2 Denali 16.2.1 Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support Release 8.0.x.
3.1.5	Denali 16.3.2 Denali 16.3.1 Denali 16.2.2 Denali 16.1.2 Denali 16.2.1 Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support Release 8.0.x.

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.1.4	Denali 16.3.1 Denali 16.1.2 Denali 16.2.2 Denali 16.2.1 Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support Release 8.0.x.
3.1.3	Denali 16.2.2 Denali 16.1.2 Denali 16.2.1 Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support Release 8.0.x.

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.1.1	Denali 16.1.2 Denali 16.2.1 Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support Release 8.0.x.
3.1	Denali 16.1.2 Denali 16.2.1 Denali 16.1.1 03.07.03E 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support Release 8.0.x.
3.0 Technology Pack	Denali 16.1.1 03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	Denali 16.x.x does not support Release 8.0.x.

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.0.2	03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	
3.0.1	03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	
3.0	03.07.002E 03.07.001E 03.07.000E 03.06.03E 03.06.02E 03.06.01E 03.06.00E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E platform (Platform support from 03.07.00.E and later).	

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
2.2.3	03.07.00E 03.06.03E 03.06.01E 03.06.00E 03.03.03S 03.03.04S 03.03.05SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	—
	03.07.00E* 03.07.01E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E	*With Release 03.07.00.1 for Cisco Catalyst 4500 S Engine 8-E platform.
2.2.2	03.07.00E 03.06.03E 03.06.01E 03.06.00E 03.03.03S 03.03.04S 03.03.05SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	—
	03.07.00E* 03.07.01E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E	*With Release 03.07.00.1 for Cisco Catalyst 4500 S Engine 8-E platform.

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
2.2	03.07.00E 03.06.03E 03.06.01E 03.06.00E 03.03.03S 03.03.04S 03.03.05SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	*With Release 03.07.00E for Cisco Catalyst 4500 Series Supervisor Engine 8-E platform.
	03.07.00E* 03.07.01E	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch Cisco Catalyst 4500 Series Switch Supervisor Engine 8-E	
2.1.2	03.06.03E 3.6.1E 3.6.0E 03.03.03S 03.03.04S 03.03.05SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	We recommend that you use Cisco Prime Infrastructure 2.1.2 if you are using Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch. We recommend that you use Cisco Prime Infrastructure 2.1 if you are using Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch or Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch.
2.1.1	3.6.0E 03.03.02SE 03.03.01SE 03.03.00SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	We recommend that you use Cisco Prime Infrastructure 2.1.1 if you are using Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch. We recommend that you use Cisco Prime Infrastructure 2.1 if you are using Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch or Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch.

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
2.1	3.6.0E 3.3.2SE 3.3.1SE 3.3.0SE 3.2.3SE 3.2.2SE	Cisco Catalyst 3850 Switch / Catalyst 38xx stack-able Ethernet Switch Cisco 5700 Series Wireless Controller / Catalyst 57xx stack-able Ethernet Switch	For Release 3.6.0E, we recommend Cisco Prime Infrastructure 2.0. If Cisco Prime Infrastructure 2.0 is not deployed, Cisco Prime Infrastructure 1.4.0.45 is recommended. If Cisco Prime Infrastructure 1.4.0.45 is not deployed, Cisco Prime Infrastructure 1.3.0.20 is recommended. If Cisco Prime Infrastructure 1.3.0.20 is not deployed, Cisco Prime Infrastructure 1.2.1.12 is recommended. If Cisco Prime Infrastructure 1.2.1.12 is not deployed, Cisco Prime Infrastructure 1.1.1.12 is recommended. If Cisco Prime Infrastructure 1.1.1.12 is not deployed, Cisco Prime Infrastructure 1.0.1.12 is recommended. If Cisco Prime Infrastructure 1.0.1.12 is not deployed, Cisco Prime Infrastructure 1.0.0.12 is recommended. If Cisco Prime Infrastructure 1.0.0.12 is not deployed, Cisco Prime Infrastructure 0.9.1.12 is recommended. If Cisco Prime Infrastructure 0.9.1.12 is not deployed, Cisco Prime Infrastructure 0.8.1.12 is recommended. If Cisco Prime Infrastructure 0.8.1.12 is not deployed, Cisco Prime Infrastructure 0.7.1.12 is recommended. If Cisco Prime Infrastructure 0.7.1.12 is not deployed, Cisco Prime Infrastructure 0.6.1.12 is recommended. If Cisco Prime Infrastructure 0.6.1.12 is not deployed, Cisco Prime Infrastructure 0.5.1.12 is recommended. If Cisco Prime Infrastructure 0.5.1.12 is not deployed, Cisco Prime Infrastructure 0.4.1.12 is recommended. If Cisco Prime Infrastructure 0.4.1.12 is not deployed, Cisco Prime Infrastructure 0.3.1.12 is recommended. If Cisco Prime Infrastructure 0.3.1.12 is not deployed, Cisco Prime Infrastructure 0.2.1.12 is recommended. If Cisco Prime Infrastructure 0.2.1.12 is not deployed, Cisco Prime Infrastructure 0.1.1.12 is recommended. If Cisco Prime Infrastructure 0.1.1.12 is not deployed, Cisco Prime Infrastructure 0.0.1.12 is recommended. If Cisco Prime Infrastructure 0.0.1.12 is not deployed, Cisco Prime Infrastructure 0.0.0.12 is recommended. If Cisco Prime Infrastructure 0.0.0.12 is not deployed, Cisco Prime Infrastructure 0.0.0.0 is recommended.
	3.6.0E 3.3.2SE 3.3.1SE 3.3.0SE	Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch	
2.0	3.3.1SE 3.3.0SE 3.2.3SE	Cisco Catalyst 3850 Switch Cisco 5700 Series Wireless Controller	Cisco Catalyst 3650 Switch / Catalyst 36xx stack-able Ethernet Switch. Cisco Catalyst 3650 Switch 3.3.xSE release is not supported for Cisco Prime Infrastructure 2.0.
	IOS12.2(50)SE IOS12.2(50)SG IOS12.2(33)SXI	Cisco Catalyst 3750 Switch	
1.4.0.45	3.2.1SE 3.2.2SE	Cisco Catalyst 3850 Switch	Can be used only for Cisco Prime Infrastructure 1.4.0.45.
	IOS12.2(50)SE IOS12.2(50)SG IOS12.2(33)SXI	Cisco Catalyst 3750 Switch	
1.3.0.20	3.2.1SE	Cisco Catalyst 3850 Switch	Can be used only for Cisco Prime Infrastructure 1.3.0.20.
	IOS12.2(50)SE IOS12.2(50)SG IOS12.2(33)SXI	Cisco Catalyst 3750 Switch	
1.2.1.12	IOS12.2(50)SE IOS12.2(50)SG IOS12.2(33)SXI	Cisco Catalyst 3750 Switch	Can be used only for Cisco Prime Infrastructure 1.2.1.12.

Cisco Prime Network Control System Compatibility Matrix

Table 14: [Cisco Prime Network Control System Compatibility Matrix](#), on page 117 lists the compatibility matrix of Cisco Prime NCS, controller, access point images, Identity Services Engines (ISE), and Cisco Mobility Services Engine (MSE).

Table 14: Cisco Prime Network Control System Compatibility Matrix

Cisco NCS	Cisco AireOS Controller	Cisco MSE	Cisco ISE
1.1.1.24	7.2.115.2	7.2.110.0	ISE 1.0
	7.2.111.3	7.2.103.0	ISE 1.1
	7.2.110.0	7.0.240.0	
	7.2.103.0	7.0.230.0	
	7.1.91.0	7.0.220.0	
	7.0.252.0	7.0.201.204	
	7.0.251.2	7.0.112.0	
	7.0.250.0	7.0.105.0	
	7.0.240.0		
	7.0.235.3		
	7.0.235.0		
	7.0.230.0		
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		

Cisco NCS	Cisco AireOS Controller	Cisco MSE	Cisco ISE
1.1.0.58	7.2.103.0	7.2.103.0	ISE 1.0
	7.0.252.0	7.0.240.0	ISE 1.1
	7.0.251.2	7.0.230.0	
	7.0.250.0	7.0.220.0	
	7.0.240.0	7.0.201.204	
	7.0.235.3	7.0.112.0	
	7.0.235.0	7.0.105.0	
	7.0.230.0		
	7.1.91.0 ¹		
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		

Cisco NCS	Cisco AireOS Controller	Cisco MSE	Cisco ISE
1.0.2.29	7.0.252.0	7.0.240.0	ISE 1.0
	7.0.251.2	7.0.230.0	
	7.0.250.0	7.0.220.0	
	7.0.240.0	7.0.201.204	
	7.0.235.3	7.0.112.0	
	7.0.235.0	7.0.105.0	
	7.0.230.0	6.0.202.0	
	7.1.91.0 ¹	6.0.103.0	
	7.0.220.0		
	7.0.116.0		
	7.0.98.218		
	7.0.98.0		
	6.0.202.0		
	6.0.199.4		
	6.0.196.0		
	6.0.188.0		
	6.0.182.0		
	6.0.108.0		
	4.2.209.0		
	4.2.207.0		
	4.2.205.0		
	4.2.176.0		
	4.2.173.0		
	4.2.130.0		
	4.2.112.0		
	4.2.99.0		
	4.2.61.0		

Cisco NCS	Cisco AireOS Controller	Cisco MSE	Cisco ISE
1.0.1.4	7.0.220.0	7.0.220.0	ISE 1.0
	7.0.116.0	7.0.201.204	
	7.0.98.218	7.0.112.0	
	7.0.98.0	7.0.105.0	
	6.0.202.0	6.0.202.0	
	6.0.199.4	6.0.103.0	
	6.0.196.0		
	6.0.188.0		
	6.0.182.0		
	6.0.108.0		
	4.2.209.0		
	4.2.207.0		
	4.2.205.0		
	4.2.176.0		
	4.2.173.0		
	4.2.130.0		
	4.2.112.0		
	4.2.99.0		
	4.2.61.0		

Cisco NCS	Cisco AireOS Controller	Cisco MSE	Cisco ISE
1.0.0.96	7.0.116.0	7.0.201.204	ISE 1.0
	7.0.98.218	7.0.112.0	
	7.0.98.0	7.0.105.0	
	6.0.202.0	6.0.202.0	
	6.0.199.4	6.0.103.0	
	6.0.196.0		
	6.0.188.0		
	6.0.182.0		
	6.0.108.0		
	4.2.209.0		
	4.2.207.0		
	4.2.205.0		
	4.2.176.0		
	4.2.173.0		
	4.2.130.0		
	4.2.112.0		
	4.2.99.0		
	4.2.61.0		

1	If you upgrade to the 7.1.91.0 software release of Cisco Wireless LAN Controller from an earlier release, we suggest that you also upgrade Cisco Wireless Control System to 7.0.220.0 and Cisco MSE to 7.0.220.0. This upgrade ensures that you get support for the latest 3600i and 3600e lightweight access points.
---	---

Cisco Wireless Control System Compatibility Matrix

Table 15: Cisco WCS Compatibility Matrix , on page 122 lists the Cisco Wireless Control System (WCS) compatibility matrix.

Table 15: Cisco WCS Compatibility Matrix

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
7.0.240.0	7.0.252.0	—	7.0.240.0	7.0.230.0
	7.0.251.2			7.0.220.0
	7.0.250.0			7.0.172.0
	7.0.240.0			7.0.164.3
	7.0.235.3			7.0.164.0
	7.0.235.0			6.0.202.0
	7.0.230.0			6.0.196.0
	7.0.220.0			6.0.181.0
	7.0.116.0			6.0.170.0
	7.0.98.218			6.0.132.0
	7.0.98.0			5.2.148.0
	6.0.202.0			5.2.130.0
	6.0.196.0			5.2.125.0
	6.0.188.0			5.2.110.0
	6.0.182.0			
	6.0.108.0			
	5.2.193.0			
	5.2.178.0			
	5.2.157.0			
	4.2.209.0			
	4.2.207.0			
	4.2.205.0			
	4.2.176.0			
	4.2.173.0			
	4.2.130.0			
	4.2.112.0			
	4.2.99.0			
	4.2.61.0			

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Support From
7.0.230.0	7.0.235.3	—	7.0.230.0	7.0.220.0
	7.0.235.0			7.0.172.0
	7.0.230.0			7.0.164.3
	7.0.220.0			7.0.164.0
	7.0.116.0			6.0.202.0
	7.0.98.218			6.0.196.0
	7.0.98.0			6.0.181.0
	6.0.202.0			6.0.170.0
	6.0.196.0			6.0.132.0
	6.0.188.0			5.2.148.0
	6.0.182.0			5.2.130.0
	6.0.108.0			5.2.125.0
	5.2.193.0			5.2.110.0
	5.2.178.0			
	5.2.157.0			
	4.2.209.0			
	4.2.207.0			
	4.2.205.0			
	4.2.176.0			
	4.2.173.0			
4.2.130.0				
4.2.112.0				
4.2.99.0				
4.2.61.0				

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
7.0.220.0	7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0 6.0.202.0 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	—	7.0.220.0	7.0.172.0 7.0.164.3 7.0.164.0 6.0.202.0 6.0.196.0 6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Support From
7.0.172.0	7.0.116.0	—	7.0.201.204	7.0.164.3
	7.0.98.218			7.0.164.0
	7.0.98.0			6.0.202.0
	6.0.202.0			6.0.196.0
	6.0.196.0			6.0.181.0
	6.0.188.0			6.0.170.0
	6.0.182.0			6.0.132.0
	6.0.108.0			5.2.148.0
	5.2.193.0			5.2.130.0
	5.2.178.0			5.2.125.0
	5.2.157.0			5.2.110.0
	4.2.209.0			
	4.2.207.0			
	4.2.205.0			
	4.2.176.0			
	4.2.173.0			
	4.2.130.0			
	4.2.112.0			
	4.2.99.0			
	4.2.61.0			

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
7.0.164.3	7.0.98.218	—	7.0.112.0	6.0.181.0
	7.0.98.0		7.0.105.0	6.0.170.0
	6.0.196.0			6.0.132.0
	6.0.188.0			5.2.148.0
	6.0.182.0			5.2.130.0
	6.0.108.0			5.2.125.0
	5.2.193.0			5.2.110.0
	5.2.178.0			
	5.2.157.0			
	4.2.209.0			
	4.2.207.0			
	4.2.205.0			
	4.2.176.0			
	4.2.173.0			
	4.2.130.0			
	4.2.112.0			
	4.2.99.0			
4.2.61.0				

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Support From
7.0.164.0	7.0.98.218	—	7.0.112.0	6.0.181.0
	7.0.98.0		7.0.105.0	6.0.170.0
	6.0.196.0		6.0.132.0	
	6.0.188.0		5.2.148.0	
	6.0.182.0		5.2.130.0	
	6.0.108.0		5.2.125.0	
	5.2.193.0		5.2.110.0	
	5.2.178.0			
	5.2.157.0			
	4.2.209.0			
	4.2.207.0			
	4.2.205.0			
	4.2.176.0			
	4.2.173.0			
	4.2.130.0			
	4.2.112.0			
	4.2.99.0			
	4.2.61.0			

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
6.0.196.0	6.0.199.4 6.0.199.0 (pulled from CCO) 6.0.196.0 6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 5.1.163.0 5.1.151.0 4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	6.0.102.0	6.0.105.0	6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 4.2.128.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Support From
6.0.181.0	6.0.199.4	6.0.101.0	6.0.103.0	6.0.170.0
	6.0.199.0			6.0.132.0
	6.0.196.159			5.2.148.0
	6.0.196.0			5.2.130.0
	6.0.188.0			5.2.125.0
	6.0.182.0			5.2.110.0
	6.0.108.0			5.1.65.4
	5.2.193.0			5.1.64.0
	5.2.178.0			4.2.128.0
	5.2.157.0			4.2.110.0
	5.1.163.0			4.2.97.0
	5.1.151.0			4.2.81.0
	4.2.207.0			4.2.62.11
	4.2.205.0			4.2.62.0
	4.2.176.0			
	4.2.173.0			
	4.2.130.0			
	4.2.112.0			
	4.2.99.0			
	4.2.61.0			

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
6.0.170.0	6.0.188.0 6.0.182.0 6.0.108.0 5.2.193.0 5.2.178.0 5.2.157.0 5.1.163.0 5.1.151.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	6.0.97.0	6.0.97.0	6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 4.2.128.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
6.0.132.0	6.0.182.0 6.0.108.0 5.2.178.0 5.2.157.0 5.1.163.0 5.1.151.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	6.0.85.0	6.0.85.0	5.2.130.0 5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 4.2.128.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Support From
5.2.148.0	5.2.193.0 5.2.178.0 5.2.157.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.2.100.0	5.2.100.0	5.2.130.0 5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.128.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
5.2.130.0	5.2.178.0 5.2.157.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.2.91.0	5.2.91.0	5.2.125.0 5.2.110.0 5.1.65.4 5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
5.2.125.0 (pulled from CCO)	5.2.178.0 5.2.157.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.2.91.0	5.2.91.0	5.2.110.0 5.1.65.4 5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
5.2.110.0	5.2.157.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.2.91.0	5.2.91.0	5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
5.1.65.4	5.1.163.0 5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.1.35.0	5.1.35.0	5.1.64.0 5.0.72.0 5.0.56.2 5.0.56.0 4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Support From
5.1.64.0	5.1.151.0 5.0.148.2 5.0.148.0 4.2.176.0 4.2.173.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0	5.1.30.0	5.1.30.0	5.0.56.2 5.0.56.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0
5.0.72.0	5.0.148.2 5.0.148.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0	4.0.38.0	—	5.0.56.2 5.0.56.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0
5.0.56.2	5.0.148.0 4.2.61.0 4.1.x.x	4.0.33.0	—	5.0.56.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0
5.0.56.0	5.0.148.0 4.2.61.0 4.1.x.x	4.0.32.0	—	4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
4.2.128.0	4.2.209.0 4.2.207.0 4.2.205.0 4.2.176.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.43.0	—	4.2.110.0 4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0
4.2.110.0	4.2.176.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.42.0	—	4.2.97.0 4.2.81.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Support From
4.2.97.0	4.2.176.0 4.2.130.0 4.2.112.0 4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.38.0	—	4.2.81.0 4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0
4.2.81.0	4.2.99.0 4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.36.0	—	4.2.62.11 4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0
4.2.62.11	4.2.61.0 4.1.185.0 4.1.171.0 4.0.216.0 4.0.206.0 4.0.179.11 4.0.179.8 4.0.155.0	3.1.35.0	—	4.2.62.0 4.1.91.0 4.1.83.0 4.0.100.0 4.0.97.0 4.0.96.0 4.0.87.0 4.0.81.0 4.0.66.0

WCS Version	AireOS Controller Versions	2710 Location Appliance Versions	MSE Versions	Upgrade Supported From
4.2.62.0	4.2.61.0	3.1.35.0	—	4.1.91.0
	4.1.185.0			4.1.83.0
	4.1.171.0			4.0.100.0
	4.0.216.0			4.0.97.0
	4.0.206.0			4.0.96.0
	4.0.179.11			4.0.87.0
	4.0.179.8			4.0.81.0
	4.0.155.0			4.0.66.0

Cisco WCS Navigator Compatibility Matrix

Cisco WCS and Cisco WCS Navigator must be from the same release in order to be compatible (see [Table 16: WCS and Navigator Compatibility Matrix](#), on page 137). Although the release numbers will not be the same, you must verify whether they were part of the same release.

For example, Cisco WCS Navigator 1.0 is compatible with Cisco WCS 4.1, and Cisco WCS Navigator 1.1.x is compatible with any Cisco WCS 4.2.x.



Note When Cisco WCS Navigator is upgraded to a new version, the corresponding Cisco WCS must also be upgraded to the corresponding new version. For example, if Cisco WCS Navigator is upgraded to version 1.6, Cisco WCS must also be upgraded to the corresponding version 7.0.

Table 16: WCS and Navigator Compatibility Matrix

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.6.230.0	7.0.240.0 7.0.230.0	1.6.220.0 1.6.172.0 1.6.164.3 1.6.164.0 1.5.202.0 1.5.196.0 1.5.181.0 1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0
1.6.220.0	7.0.220.0	1.6.172.0 1.6.164.3 1.6.164.0 1.5.202.0 1.5.196.0 1.5.181.0 1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.6.172.0	7.0.172.0	1.6.164.3 1.6.164.0 1.5.202.0 1.5.196.0 1.5.181.0 1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0
1.6.164.3	7.0.164.3	1.6.164.0 1.5.202.0 1.5.196.0 1.5.181.0 1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0
1.6.164.0	7.0.164.0 7.0.164.3	6.0.181.0 6.0.170.0 6.0.132.0 5.2.148.0 5.2.130.0 5.2.125.0 5.2.110.0

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.5.202.0	6.0.132.0 6.0.181.0 6.0.202.0	1.5.196.0 1.5.181.0 1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.5.196.0	6.0.196.0	1.5.181.0 1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.5.181.0	6.0.181.0	1.5.170.0 1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.5.170.0	6.0.132.0	1.5.132.0 1.4.148.0 1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.5.132.0	6.0.132.0	1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.4.148.0	5.2.148.0	1.4.130.0 1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.2.72.0 1.2.56.2 1.2.56.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.4.130.0	5.2.130.0 5.2.110.0	1.4.125.0 1.4.110.0 1.3.65.4 1.3.64.0 1.2.72.0 1.2.56.2 1.2.56.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.4.110.0	5.2.110.0	1.3.64.0 1.2.72.0 1.2.56.2 1.2.56.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0
1.3.64.0	5.1.64.0	1.2.56.2 1.2.56.0 1.1.128.0 1.1.110.0 1.1.97.0 1.1.81.0 1.1.62.11 1.1.62.0

Navigator Release Number	WCS Release Number	Upgrade Supported From
1.1.128.0	4.2.97.0	1.1.110.0
	4.2.81.0	1.1.97.0
	4.2.62.11	1.1.81.0
	4.2.62.0	1.1.62.11
	4.2.110.0	1.1.62.0
	4.2.128.0	1.0.91.0 1.0.83.0
1.1.110.0	4.2.97.0	1.1.97.0
	4.2.81.0	1.1.81.0
	4.2.62.11	1.1.62.11
	4.2.62.0	1.1.62.0
	4.2.110.0	1.0.91.0 1.0.83.0
1.1.97.0	4.2.97.0	1.1.81.0
	4.2.81.0	1.1.62.11
	4.2.62.11	1.1.62.0
	4.2.62.0	1.0.91.0 1.0.83.0
1.1.62.11	4.2.62.11	1.1.62.0
	4.2.62.0	1.0.91.0 1.0.83.0
1.1.62.0	4.2.62.0	1.0.91.0 1.0.83.0
1.0.91.0	4.1.91.0	1.0.83.0
	4.1.83.0	
1.0.83.0	4.1.83.0	—

Cisco Mobility Services Engine Compatibility Matrix

Information in this section cites cross-platform compatibility testing performed from only the Cisco MSE perspective and is limited to up to specific product releases cited in this section.

Important Notes

Information in this section cites cross-platform compatibility testing performed from only the Cisco MSE perspective and is limited to up to specific product releases cited in this section.

For Cisco MSE compatibility with Cisco Prime Infrastructure releases, see the applicable [Cisco Prime Infrastructure release notes](#).

General:

- ISE 2.x or ISE 1.4 only works with Cisco MSE Release 8.0 or earlier.
- Cisco MSE release 7.5 or later is not bundled with AeroScout CLE. However, AeroScout CLE is compatible with Cisco MSE Release 7.5 or later, which uses the API interface.
- This compatibility matrix lists only the compatibility information of Cisco MSE with other Cisco wireless products. This matrix does not reflect compatibility information between Cisco Controller and Cisco Prime Infrastructure or Cisco NCS. For compatibility information about Cisco Prime Infrastructure with Cisco Controller and other wireless products, see the *Cisco Prime Infrastructure Release Notes*.

Cisco Prime Infrastructure

- Cisco MSE Release 8.0.140.x or later is compatible with Cisco Prime Infrastructure Releases 3.1.7, 3.1.6, 3.1.5, 3.1.3, 3.1.1, 3.0.3.1, and 2.2.3.5. If you encounter reachability issues with the Cisco MSE, upgrade to Prime Infrastructure Release 3.1.3. (CSCuz19013)
- For Cisco MSE Release 8.0.x HA and Controller Release 8.0 or later, Prime Infrastructure Release 2.2.x is compatible.
- Cisco MSE 3365 supports Cisco Prime Infrastructure 2.1.1 or later. Cisco MSE 3365 does not support Cisco Prime Infrastructure 2.1.0.

Cisco Access Points

- Cisco MSE Release 8.0.140.9 and later includes wIPS and CAS support for the Cisco Aironet 1800, 2800, 3800, and 4800 series.

Catalyst Switches

- Cisco MSE platforms running Cisco MSE Release 8.x are not compatible with the following Cisco switch platforms:
 - Cisco Catalyst 2960-24TT switch running Cisco Release 15.0(2)SE11
 - Cisco Catalyst 2960-48-PST-L switch running Cisco Release 15.0(2)SE11
 - Cisco Catalyst 2960X-24PS-L switch running Cisco Release 15.2(2)E7
 - Cisco Catalyst 3650-24PS switch running Cisco Release 16.3.5b
 - Cisco Catalyst 3560-24PS switch running Cisco Release 12.2(55)SE11
 - Cisco Catalyst 3850-24XS switch running Cisco Release 16.3.5.b
 - Cisco Nexus 5596UP switch running Cisco Release 7.1(4)N1(1)

Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x

Information in this section cites cross-platform compatibility testing performed from only the Cisco MSE perspective and is limited to up to specific product releases cited in this section.

For Cisco MSE compatibility with Cisco Prime Infrastructure releases, see the applicable [Cisco Prime Infrastructure release notes](#).

Table 17: Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
8.0.150.x	8.0.150.x	8.0.150.x	3.9.1		3.7.x
			3.8.x		3.6.x
			3.7.x		3.3.5
			3.6.x		3.3.4
			3.5.x		3.3.3
			3.4.x		3.3.2
			3.3.1		3.3.0
			3.3		3.2.3
			3.2.2		3.2.2
			3.2.1		3.2.0
			3.2		3.1.6
			3.1.7		
			3.1.6		
			3.1.5		
			3.1.3		
			3.1		
			3.0.3		
			2.2.3		

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				8.5.12x.0	
				8.5.11x.0	
				8.5.10x.0	
				8.4.10x.0	
				8.3.14x.0	
				8.3.13x.0	
				8.3.12x.0	
				8.3.112.0	
				8.3.111.0	
				8.3.102.0	
				8.2.16x.0	
				8.2.160.0	
				8.2.151.0	
				8.2.141.0	
				8.2.130.0	
				8.2.121.0	
				8.2.111.0	
				8.2.110.0	
				8.1.131.0	
				8.1.122.0	
				8.1.111.0	
				8.1.102.0	
				8.0.15x.0	
				8.0.140.0	
				8.0.13x.0	
				8.0.121.0	
				8.0.120.0	
				8.0.110.0	
				8.0.100.0	
				7.6.130.0*	
				7.6.120.0*	
				7.6.110.0*	
				7.6.100.0*	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				7.5.102.0** 7.4.121.0** 7.4.110.0** 7.4.100.60** 7.4.100.0** 7.3.112.0** 7.3.101.0** 7.2.111.3** 7.2.110.0** 7.2.103.0** 7.0.240.0** 7.0.235.3** 7.0.235.0** 7.0.230.0** 7.1.91.0** 7.0.220.0** 7.0.116.0** 7.0.98.218** 7.0.98.0**	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
8.0.140.x	8.0.140.x	8.0.140.x	3.4.x 3.3.1 3.3 3.2.2 3.2.1 3.2 3.1.7 3.1.6 3.1.5 3.1.3 3.1 3.0.3 2.2.3		3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.3.0 3.2.3 3.2.2 3.2.0 3.1.6

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				8.5.12x.0	
				8.5.11x.0	
				8.5.10x.0	
				8.4.10x.0	
				8.3.14x.0	
				8.3.13x.0	
				8.3.12x.0	
				8.3.112.0	
				8.3.111.0	
				8.3.102.0	
				8.2.16x.0	
				8.2.160.0	
				8.2.151.0	
				8.2.141.0	
				8.2.130.0	
				8.2.121.0	
				8.2.111.0	
				8.2.110.0	
				8.1.131.0	
				8.1.122.0	
				8.1.111.0	
				8.1.102.0	
				8.0.15x.0	
				8.0.140.0	
				8.0.13x.0	
				8.0.121.0	
				8.0.120.0	
				8.0.110.0	
				8.0.100.0	
				7.6.130.0*	
				7.6.120.0*	
				7.6.110.0*	
				7.6.100.0*	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				7.5.102.0** 7.4.121.0** 7.4.110.0** 7.4.100.60** 7.4.100.0** 7.3.112.0** 7.3.101.0** 7.2.111.3** 7.2.110.0** 7.2.103.0** 7.0.240.0** 7.0.235.3** 7.0.235.0** 7.0.230.0** 7.1.91.0** 7.0.220.0** 7.0.116.0** 7.0.98.218** 7.0.98.0**	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
8.0.130.0	8.0.130.0	8.0.130.0	3.1 3.0.1 3.0 2.2 and later 1.4***		3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				8.3.13x.0	
				8.3.111.0	
				8.3.102.0	
				8.2.16x.0	
				8.2.151.0	
				8.2.141.0	
				8.2.130.0	
				8.2.121.0	
				8.2.111.0	
				8.2.110.0	
				8.1.131.0	
				8.1.122.0	
				8.1.111.0	
				8.1.102.0	
				8.0.15x.0	
				8.0.140.0	
				8.0.13x.0	
				8.0.121.0	
				8.0.120.0	
				8.0.110.0	
				8.0.100.0	
				7.6.130.0*	
				7.6.120.0*	
				7.6.110.0*	
				7.6.100.0*	
				7.5.102.0**	
				7.4.121.0**	
				7.4.110.0**	
				7.4.100.60**	
				7.4.100.0**	
				7.3.112.0**	
				7.3.101.0**	
				7.2.111.3**	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				7.2.110.0** 7.2.103.0** 7.0.240.0** 7.0.235.3** 7.0.235.0** 7.0.230.0** 7.1.91.0** 7.0.220.0** 7.0.116.0** 7.0.98.218** 7.0.98.0**	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
8.0.120.7	8.0.120.7	8.0.120.7	3.0.1 3.0 2.2.2*** 2.2.1 2.2 2.1.2*** 2.1.1*** 1.4*****		3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				8.1.131.0	
				8.1.122.0	
				8.1.111.0	
				8.1.102.0	
				8.0.15x.0	
				8.0.140.0	
				8.0.13x.0	
				8.0.121.0	
				8.0.120.0	
				8.0.110.0	
				8.0.100.0	
				7.6.130.0	
				7.6.120.0	
				7.6.110.0*	
				7.6.100.0*	
				7.5.102.0****	
				7.4.150.0****	
				7.4.140.0****	
				7.4.130.0****	
				7.4.121.0****	
				7.4.110.0****	
				7.4.100.60****	
				7.4.100.0****	
				7.3.112.0****	
				7.3.101.0****	
				7.2.111.3****	
				7.2.110.0****	
				7.2.103.0****	
				7.0.240.0****	
				7.0.235.3****	
				7.0.235.0****	
				7.0.230.0****	
				7.1.91.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				7.0.220.0**** 7.0.116.0**** 7.0.98.218**** 7.0.98.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
8.0.120.0	8.0.120.0	8.0.120.0	3.0.1 3.0 2.2.2*** 2.2.1 2.2 2.1.2*** 2.1.1*** 1.4*****		3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				8.1.131.0	
				8.1.122.0	
				8.1.111.0	
				8.1.102.0	
				8.0.15x.0	
				8.0.140.0	
				8.0.13x.0	
				8.0.121.0	
				8.0.120.0	
				8.0.110.0	
				8.0.100.0	
				7.6.130.0	
				7.6.120.0	
				7.6.110.0*	
				7.6.100.0*	
				7.5.102.0****	
				7.4.150.0****	
				7.4.140.0****	
				7.4.130.0****	
				7.4.121.0****	
				7.4.110.0****	
				7.4.100.60****	
				7.4.100.0****	
				7.3.112.0****	
				7.3.101.0****	
				7.2.111.3****	
				7.2.110.0****	
				7.2.103.0****	
				7.0.240.0****	
				7.0.235.3****	
				7.0.235.0****	
				7.0.230.0****	
				7.1.91.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				7.0.220.0**** 7.0.116.0**** 7.0.98.218**** 7.0.98.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
8.0.110.0	—	8.0.110.0	2.2.1 2.2 2.1.2*** 2.1.1*** 2.1*** 2.0*** 1.4*****		3.7.x 3.6.x 3.3.x 3.2.x

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				8.1.131.0	
				8.1.122.0	
				8.1.111.0	
				8.1.102.0	
				8.0.15x.0	
				8.0.140.0	
				8.0.13x.0	
				8.0.121.0	
				8.0.120.0	
				8.0.115.0	
				8.0.110.0	
				8.0.100.0	
				7.6.130.0	
				7.6.120.0	
				7.6.110.0*	
				7.6.100.0*	
				7.5.102.0****	
				7.4.150.0****	
				7.4.140.0****	
				7.4.130.0****	
				7.4.121.0****	
				7.4.110.0****	
				7.4.100.60****	
				7.4.100.0****	
				7.3.112.0****	
				7.3.101.0****	
				7.2.111.3****	
				7.2.110.0****	
				7.2.103.0****	
				7.0.240.0****	
				7.0.235.3****	
				7.0.235.0****	
				7.0.230.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				7.1.91.0**** 7.0.220.0**** 7.0.116.0**** 7.0.98.218**** 7.0.98.0**** 7.0.250.0 7.0.251.0 7.0.252.0	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
8.0.100.0*	—	8.0.100.0	2.2.1 2.2 2.1.2 2.1.1*** 2.1 2.0 1.4*****	8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.100.0 7.6.130.0 7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0**** 7.4.150.0**** 7.4.140.0**** 7.4.130.0**** 7.4.121.0**** 7.4.110.0**** 7.4.100.60**** 7.4.100.0**** 7.3.112.0**** 7.3.101.0**** 7.2.111.3**** 7.2.110.0**** 7.2.103.0**** 7.0.240.0**** 7.0.235.3**** 7.0.235.0**** 7.0.230.0**** 7.1.91.0**** 7.0.220.0**** 7.0.116.0**** 7.0.98.218**** 7.0.98.0****	3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
7.6.120.0	—	7.6.120.0	2.2.1 2.2 2.1.2 2.1.1** 2.1 2.0 1.4.2	7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
7.6.132.0	—	7.6.132.0	2.2.1 2.2 2.1.2 2.1.1** 2.1 2.0 1.4.2	7.6.130.0 7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
7.6.100.0	—	7.6.100.0	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0 Update 1 for 1.4.0.45* Update 2 for 1.4.0.45**	7.6.110.0* 7.6.100.0* 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
7.6.100.0	—	7.6.100.0	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0*	7.6.110.0** 7.6.100.0** 7.5.102.0** 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	3.2.2** 3.3.2**

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
7.5.102.101	—	7.5.102.101	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0 Update 1 for 1.4.0.45 1.4.0.45	7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
7.5.102.101	—	7.5.102.101	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0*	7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	3.2.2** 3.3.2**

Cisco MSE Compatibility Matrix for Legacy Software Versions

Information in this section cites cross-platform compatibility testing performed from only the Cisco MSE perspective and is limited to up to specific product releases cited in this section.

For Cisco MSE compatibility with Cisco Prime Infrastructure releases, see the applicable Cisco Prime Infrastructure release notes at:

<https://www.cisco.com/c/en/us/support/cloud-systems-management/prime-infrastructure/products-release-notes-list.html>

Table 18: Cisco MSE Compatibility Matrix—Legacy Software Versions

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controlle
7.4.121.0	—	7.4.121.0	4.5.2.16 4.4.2.11	—	7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.6 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.21 7.0.98.0

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controller
7.4.110.0	—	7.4.110.0	4.4.2.11	—	7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0
7.4.100.0	—	7.4.100.0	4.4.2.114.4.2.7	—	7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controlle
7.3.101.0	7.3.101.0	7.3.101.0	4.4.2.4	—	7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.6 7.4.100.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.21 7.0.98.0
7.2.110.0	7.2.110.0	7.2.110.0	4.4.2.4	—	7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.21 7.0.98.0

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controller
7.2.103.0	7.2.103.0	7.2.103.0	4.4.1.4	—	7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0
7.0.240.0	7.0.240.0	—	4.3.1.10	7.0.240.0	7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0
7.0.230.0	7.0.230.0	—	4.3.1.19	7.0.230.0	7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controlle
7.0.220.0	7.0.220.0	—	4.3.1.19	7.0.220.0	7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.21 7.0.98.0
7.0.201.204	7.0.201.204	—	4.2.4.4	7.0.172.0	7.0.116.0 7.0.98.21 7.0.98.0
7.0.112.0	7.0.112.0	—	4.2.4.4	7.0.164.3 7.0.164.0	7.0.98.21 7.0.98.0

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controller
7.0.105.0	7.0.105.0	—	4.2.4.4	7.0.164.3	7.0.98.218

Cisco Support Community

Cisco Support Community is a forum for you to ask and answer questions, share suggestions, and collaborate with your peers. Join the forum at: <https://supportforums.cisco.com/index.jspa>

Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions, and services, visit [Cisco DevNet](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

Cisco Bug Search Tool

[Cisco Bug Search Tool](#) (BST) is a gateway to the Cisco bug-tracking system, which maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. The BST provides you with detailed defect information about your products and software.

Documentation Feedback

To provide feedback about Cisco technical documentation, use the feedback form available in the right pane of every online document.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2023 Cisco Systems, Inc. All rights reserved.