

UCS C-Series 서버 재부팅 문제 해결 TechNote

목차

[소개](#)

[사전 요구 사항](#)

[요구 사항](#)

[사용되는 구성 요소](#)

[다른 재부팅 조건에 대한 예상 출력](#)

[OS에서 재부팅\(vSphere 5.0\)](#)

[CIMC 사용자 인터페이스의 전원 주기](#)

[CIMC 사용자 인터페이스에서 전원 끄기](#)

[CIMC 사용자 인터페이스에서 전원 켜기](#)

[서버 전면의 전원 버튼\(OFF\)](#)

[서버 전면의 전원 버튼\(ON\)](#)

소개

이 문서에서는 서로 다른 재부팅 조건의 예상 출력을 보여 주는 C210-M2에 대한 /var/log/messages(OBFL(Onboard Failure Logging) 로그에도 있음)의 출력을 제공합니다. Cisco UCS(Unified Computing System) C-Series 서버 부팅 문제를 해결할 때, 시작할 수 있는 한 곳은 /var/log/messages 및 OBFL 로그입니다. 이러한 로그는 기술 지원 파일에 있습니다. 이 아이디어는 특정 기술 지원 메시지의 출력을 이 문서의 출력과 일치시켜 재부팅을 트리거한 항목을 확인할 수 있다는 것입니다.

사전 요구 사항

요구 사항

다음 주제에 대한 지식을 보유하고 있으면 유용합니다.

- VMware vSphere 5.0
- Cisco CIMC(Integrated Management Controller)

사용되는 구성 요소

이 문서는 특정 소프트웨어 및 하드웨어 버전으로 한정되지 않습니다.

이 문서의 정보는 특정 랩 환경의 디바이스를 토대로 작성되었습니다. 이 문서에 사용된 모든 디바이스는 초기화된(기본) 컨피그레이션으로 시작되었습니다. 현재 네트워크가 작동 중인 경우, 모든 명령어의 잠재적인 영향을 미리 숙지하시기 바랍니다.

다른 재부팅 조건에 대한 예상 출력

OS에서 재부팅(vSphere 5.0)

5:2012 May 11 13:49:38:BMC:kernel:--:<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:49:38:BMC:kernel:--:<7>[peci_init_hardware]:490:peci:
unregistered IRQ: [13]
7:2012 May 11 13:49:38:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:49:38:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0002 files.
5:2012 May 11 13:49:38:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
/var/nuova/BIOS/BiosTech_1.txt
5:2012 May 11 13:49:38:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
/var/nuova/BIOS/BiosTech_4.txt
5:2012 May 11 13:49:38:BMC:kernel:--:<5>[block_transfer_fetch_host_request_for_app]:
2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 126 : FName = BiosTech_1.txt
5:2012 May 11 13:49:38:BMC:kernel:--:<5>[block_transfer_fetch_host_request_for_app]:
2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 125 : FName = BiosTech_4.txt
5:2012 May 11 13:49:38:BMC:kernel:--:<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 13:49:38:BMC:kernel:--:<7>[peci_init_hardware]:472:peci:
registered IRQ: [13]
5:2012 May 11 13:49:38:BMC:kernel:--:<5>[lpc_reset_handler_Port80_Capture_setup]:
630:BIOS_POST_CMPLT De-asserted --> BIOS is running
7:2012 May 11 13:49:38:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:49:38:BMC:kernel:--:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0000 files.
6:2012 May 11 13:49:38:BMC:avct_server:--: rvas_wait_for_changes failed
4:2012 May 11 13:49:38:BMC:avct_server:--: No Video Source Detected!
5:2012 May 11 13:49:39:BMC:bioscom:--: lv_mode_dimm_support.c:126:
[lpc_reset_seen]LPC Reset Count is Different [0x28:0x29]
Asserted LPC Reset Seen
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
Fn:0x4 Cmd:0x28 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data: 0x9 0x80
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
Fn:0x4 Cmd:0x28 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data: 0xa 0x80
5:2012 May 11 13:49:39:BMC:bioscom:--: lv_mode_dimm_support.c:197:
[transition_function]Starting Transition to
[High Voltage Mode] from [Unknown Mode]
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
Fn:0x4 Cmd:0x28 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data: 0x9 0x80
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
Fn:0x4 Cmd:0x28 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data: 0xa 0x80
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
Fn:0x4 Cmd:0x26 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data:
0x9 0x36 0x92 0x92 0x89 0x9f 0x9f 0xa8
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
Fn:0x4 Cmd:0x26 Resp:0x0
5:2012 May 11 13:49:39:BMC:IPMI:585: Bridge.c:1415:audit data:
0xa 0x36 0x92 0x92 0x89 0x9f 0x9f 0xa8
5:2012 May 11 13:49:39:BMC:bioscom:--: lv_mode_dimm_support.c:217:
[transition_function]Transition to [High Voltage Mode] Success
5:2012 May 11 13:49:39:BMC:IPMI:591: VirtualSEL.c:224:SEL Evt[04 00]<
04 00 02 F3 18 AD 4F 20 00 04 25 53 08 00 FF FF >
5:2012 May 11 13:49:39:BMC:BIOSReader:391: BIOSReader.c:227:File Open :
BiosTech_3.txt
5:2012 May 11 13:49:39:BMC:kernel:--:<5>[block_transfer_fetch_host_request_for_app]:
2063:block_transfer_fetch_host_request_for_app: BT_OPEN:

```

HostDescriptor = 131 : Filename = BiosTech_3.txt
7:2012 May 11 13:49:39:BMC:kernel:-:<7>[mailbox_isr]:276:
Mailbox[0] Bit Change w/NULL Handler (01 - 10)!
7:2012 May 11 13:49:39:BMC:kernel:-:<7>[mailbox_isr]:276:
Mailbox[0] Bit Change w/NULL Handler (01 - 20)!
7:2012 May 11 13:49:39:BMC:kernel:-:<7>[mailbox_isr]:276:
Mailbox[0] Bit Change w/NULL Handler (01 - 40)!
5:2012 May 11 13:49:39:BMC:kernel:-:<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:49:39:BMC:kernel:-:<7>[peci_init_hardware]:490:peci:
unregistered IRQ: [13]
7:2012 May 11 13:49:39:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:49:39:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0001 files.
5:2012 May 11 13:49:39:BMC:kernel:-:<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 13:49:39:BMC:kernel:-:<7>[peci_init_hardware]:472:peci:
registered IRQ: [13]

```

참고:

- OS 부팅만 "do_power" 출력을 인쇄하지 않습니다. 서버가 OS로 부팅되었는지 신속하게 확인하기 위해 이 사실을 사용할 수 있습니다.
- OS 부팅만 [고전압 모드] 전환이 인쇄됩니다.

CIMC 사용자 인터페이스의 전원 주기

```

5:2012 May 11 13:50:22:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
Fn:0x0 Cmd:0x2 Resp:0x0
5:2012 May 11 13:50:22:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0x2
7:2012 May 11 13:50:22:BMC:kernel:-:<7>[do_power_off]:188:do_power_off
5:2012 May 11 13:50:22:BMC:kernel:-:<5>[do_power_off]:190:Power Driver:
Power Off Logic @ 181790792
6:2012 May 11 13:50:22:BMC:kernel:-:<6>[press_button]:105:Power Driver:
Press Power Button @ 181790793
5:2012 May 11 13:50:22:BMC:AUDIT:-: Server power state modify (op:power-cycle)
5:2012 May 11 13:50:26:BMC:kernel:-:<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:50:26:BMC:kernel:-:<7>[peci_init_hardware]:490:peci:
unregistered IRQ: [13]
7:2012 May 11 13:50:26:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:50:26:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0001 files.
7:2012 May 11 13:50:26:BMC:kernel:-:<7>USB FS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 13:50:26:BMC:kernel:-:<7>kbd_complete: -108, 0/8
7:2012 May 11 13:50:26:BMC:kernel:-:<7>mouse_complete: -108, 0/6
7:2012 May 11 13:50:26:BMC:kernel:-:<7>USB HS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 13:50:26:BMC:kernel:-:<7>bulk_out_complete: -108, 0/31, LUN[0][2]
7:2012 May 11 13:50:26:BMC:kernel:-:<7>handle_exception: Handling
MSD_STATE_DISCONNECT for interface[0]
7:2012 May 11 13:50:26:BMC:kernel:-:<7>do_set_interface(): reset_interface
7:2012 May 11 13:50:26:BMC:kernel:-:<7>handle_exception:
Handling MSD_STATE_DISCONNECT for interface[1]
5:2012 May 11 13:50:26:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:
2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 132 : FName = BiosTech_4.txt
6:2012 May 11 13:50:26:BMC:kernel:-:<6>kbdmouse_write:
kbd write aborted for device reset.
6:2012 May 11 13:50:26:BMC:kernel:-:<6>kbdmouse_write:
mouse write aborted for device reset.
6:2012 May 11 13:50:26:BMC:avct_server:-: rvas_wait_for_changes failed
5:2012 May 11 13:50:26:BMC:BIOSReader:391:

```

CIMC 사용자 인터페이스에서 전원 끄기

```
5:2012 May 11 13:58:57:BMC:IPMI:585: Bridge.c:1388:audit from:kcs
    Fn:0x0 Cmd:0x2 Resp:0x0
7:2012 May 11 13:58:57:BMC:kernel:--<7>[do_power_off]:188:do_power_off
5:2012 May 11 13:58:57:BMC:kernel:--<5>[do_power_off]:190:Power Driver:
    Power Off Logic @ 182297296
6:2012 May 11 13:58:57:BMC:kernel:--<6>[press_button]:105:Power Driver:
    Press Power Button @ 182297296
5:2012 May 11 13:58:57:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0x0
5:2012 May 11 13:58:57:BMC:AUDIT:-- Server power state modify (op:power-off)
5:2012 May 11 13:59:01:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:59:01:BMC:kernel:--<7>[peci_init_hardware]:490:peci:
    unregistered IRQ: [13]
7:2012 May 11 13:59:01:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
    1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:59:01:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
    1185:block_transfer_deallocate_entire_list : Dumped: 0x0002 files.
7:2012 May 11 13:59:01:BMC:kernel:--<7>USB FS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 13:59:01:BMC:kernel:--<7>USB HS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 13:59:01:BMC:kernel:--<7>bulk_out_complete: -108, 0/31, LUN[0][2]
7:2012 May 11 13:59:01:BMC:kernel:--<7>handle_exception: Handling
    MSD_STATE_DISCONNECT for interface[0]
7:2012 May 11 13:59:01:BMC:kernel:--<7>do_set_interface(): reset_interface
7:2012 May 11 13:59:01:BMC:kernel:--<7>handle_exception: Handling
    MSD_STATE_DISCONNECT for interface[1]
5:2012 May 11 13:59:01:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
    2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
    HostBTDescr = 143 : FName = BiosTech_3.txt
5:2012 May 11 13:59:01:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
    2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
    HostBTDescr = 142 : FName = BiosTech_2.txt
6:2012 May 11 13:59:01:BMC:avct_server:-- rvas_wait_for_changes failed
5:2012 May 11 13:59:01:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
    /var/nuova/BIOS/BiosTech_3.txt
5:2012 May 11 13:59:01:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
    /var/nuova/BIOS/BiosTech_2.txt
```

CIMC 사용자 인터페이스에서 전원 켜기

```
5:2012 May 11 13:59:13:BMC:IPMI:585: Bridge.c:1388:audit from:
    kcs Fn:0x0 Cmd:0x2 Resp:0x0
5:2012 May 11 13:59:13:BMC:IPMI:585: Bridge.c:1415:audit data&colon; 0x1
7:2012 May 11 13:59:13:BMC:kernel:--<7>[do_power_on]:226:do_power_on
5:2012 May 11 13:59:13:BMC:kernel:--<5>[do_power_on]:231:Power Driver:
    Power On Logic Pulse for 250ms @ 182313079
6:2012 May 11 13:59:13:BMC:kernel:--<6>[press_button]:105:Power Driver:
    Press Power Button @ 182313079
5:2012 May 11 13:59:13:BMC:AUDIT:-- Server power state modify (op:power-on)
6:2012 May 11 13:59:13:BMC:kernel:--<6>[release_button]:115:Power Driver:
    Release Power Button @ 182313330
7:2012 May 11 13:59:13:BMC:kernel:--<7>USB FS: VDD Power WAKEUP-
    Power Good = ON
6:2012 May 11 13:59:13:BMC:kernel:--<6>se_pilot2_udc_usb_turnon:
    Passed USB1.1 register test (0)
7:2012 May 11 13:59:13:BMC:kernel:--<7>USB HS: VDD Power WAKEUP-
    Power Good = ON
6:2012 May 11 13:59:13:BMC:kernel:--<6>se_pilot2_udc_usb_turnon:
    Passed USB2.0 register test (11)
```

```
5:2012 May 11 13:59:13:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 13:59:13:BMC:kernel:--<7>[peci_init_hardware]:472:peci:
  registered IRQ: [13]
5:2012 May 11 13:59:13:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]:
  630:BIOS_POST_CMPLT De-asserted --> BIOS is running
7:2012 May 11 13:59:13:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:59:13:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1185:block_transfer_deallocate_entire_list : Dumped: 0x0000 files.
5:2012 May 11 13:59:13:BMC:IPMI:587: Pilot2SrvPower.c:394:
  Blade Power Changed To: [ ON ]
5:2012 May 11 13:59:13:BMC:kernel:--<5>[do_power_on]:
  251:Power Driver: Power On Logic Done @ 182313832
5:2012 May 11 13:59:13:BMC:IPMI:590: Pilot2SrvPower.c:
  188:Pilot2SrvPowerOn
5:2012 May 11 13:59:14:BMC:IPMI:591: VirtualSEL.c:224:
  SEL Evt[25 00]< 25 00 02 32 1B AD 4F 20 00 04 25 52 08 01 FF FF >
5:2012 May 11 13:59:14:BMC:IPMI:591: VirtualSEL.c:224:
  SEL Evt[26 00]< 26 00 02 32 1B AD 4F 20 00 04 25 53 08 00 FF FF >
5:2012 May 11 13:59:14:BMC:IPMI:591: VirtualSEL.c:224:
  SEL Evt[27 00]< 27 00 02 32 1B AD 4F 20 00 04 08 62 0B 00 FF FF >
5:2012 May 11 13:59:14:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
  2063:block_transfer_fetch_host_request_for_app: BT_OPEN:
  HostDescriptor = 148 : Filename = BiosTech_1.txt
5:2012 May 11 13:59:14:BMC:BIOSReader:391: BIOSReader.c:227:
  File Open : BiosTech_1.txt
7:2012 May 11 13:59:14:BMC:kernel:--<7>[mailbox_isr]:276:
  Mailbox[0] Bit Change w/NULL Handler (01 - 10)!
7:2012 May 11 13:59:14:BMC:kernel:--<7>[mailbox_isr]:276:
  Mailbox[0] Bit Change w/NULL Handler (01 - 20)!
7:2012 May 11 13:59:14:BMC:kernel:--<7>[mailbox_isr]:276:
  Mailbox[0] Bit Change w/NULL Handler (01 - 40)!
5:2012 May 11 13:59:14:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 13:59:14:BMC:kernel:--<7>[peci_init_hardware]:490:peci:
  unregistered IRQ: [13]
7:2012 May 11 13:59:14:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1141:block_transfer_deallocate_entire_list
7:2012 May 11 13:59:14:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1185:block_transfer_deallocate_entire_list : Dumped: 0x0001 files.
6:2012 May 11 13:59:14:BMC:avct_server:--: Clear RVAS regs
5:2012 May 11 13:59:14:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 0
```

서버 전면의 전원 버튼(OFF)

```
6:2012 May 11 14:01:51:BMC:storage:--: SLOT-5:
  Time established as 05/11/12 14:01:27; (75 seconds since power on)
6:2012 May 11 14:01:51:BMC:avct_server:--:
  rvas_wait_for_changes failed
5:2012 May 11 14:01:51:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 14:01:51:BMC:kernel:--<7>[peci_init_hardware]:490:peci:
  unregistered IRQ: [13]
7:2012 May 11 14:01:51:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1141:block_transfer_deallocate_entire_list
7:2012 May 11 14:01:51:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
  1185:block_transfer_deallocate_entire_list : Dumped: 0x0002 files.
7:2012 May 11 14:01:51:BMC:kernel:--<7>USB FS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 14:01:51:BMC:kernel:--<7>USB HS: VDD Power WAKEUP- Power Good = OFF
7:2012 May 11 14:01:51:BMC:kernel:--<7>bulk_out_complete: -108, 0/31, LUN[0][0]
7:2012 May 11 14:01:51:BMC:kernel:--<7>handle_exception: Handling
  MSD_STATE_DISCONNECT for interface[0]
7:2012 May 11 14:01:51:BMC:kernel:--<7>do_set_interface(): reset_interface
7:2012 May 11 14:01:51:BMC:kernel:--<7>handle_exception: Handling
```

```
MSD_STATE_DISCONNECT for interface[1]
5:2012 May 11 14:01:51:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
/var/nuova/BIOS/BiosTech_3.txt
5:2012 May 11 14:01:51:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
/var/nuova/BIOS/BiosTech_2.txt
5:2012 May 11 14:01:51:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 150 : FName = BiosTech_3.txt
5:2012 May 11 14:01:51:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 149 : FName = BiosTech_2.txt
5:2012 May 11 14:01:51:BMC:IPMI:593: Pilot2SrvPower.c:394:
Blade Power Changed To: [ OFF ]
5:2012 May 11 14:01:51:BMC:IPMI:591: VirtualSEL.c:224:SEL Evt[33 00]<
33 00 02 CF 1B AD 4F 20 00 04 25 52 08 00 FF FF >
6:2012 May 11 14:01:51:BMC:IPMI:583: mcddI2CDrv.c:860:PI2CPerformOP:
ioctl to driver failed to read Bus[f4].Dev[5e]!  ErrorStatus[32]
6:2012 May 11 14:01:52:BMC:IPMI:583: mcddI2CDrv.c:860:PI2CPerformOP:
ioctl to driver failed to read Bus[f4].Dev[5e]!  ErrorStatus[32]
4:2012 May 11 14:01:52:BMC:avct_server:--: No Video Source Detected!
6:2012 May 11 14:01:52:BMC:avct_server:--: Video Source Detected!
5:2012 May 11 14:01:52:BMC:IPMI:591: VirtualSEL.c:224:
SEL Evt[34 00]< 34 00 02 D0 1B AD 4F 20 00 04 25 53 08 01 FF FF >
5:2012 May 11 14:01:52:BMC:bioscom:--: lv_mode_dimm_support.c:126:
[lpc_reset_seen]LPC Reset Count is Different [0x30:0x31]
Asserted LPC Reset Seen
```

서버 전면의 전원 버튼(ON)

```
5:2012 May 11 14:01:58:BMC:IPMI:591: VirtualSEL.c:224:
SEL Evt[35 00]< 35 00 02 D6 1B AD 4F 20 00 04 08 62 0B 00 FF FF >
7:2012 May 11 14:01:58:BMC:kernel:--<7>USB FS: VDD Power WAKEUP-
Power Good = ON
6:2012 May 11 14:01:58:BMC:kernel:--<6>se_pilot2_udc_usb_turnon:
Passed USB1.1 register test (0)
7:2012 May 11 14:01:58:BMC:kernel:--<7>USB HS: VDD Power WAKEUP-
Power Good = ON
6:2012 May 11 14:01:58:BMC:kernel:--<6>se_pilot2_udc_usb_turnon:
Passed USB2.0 register test (11)
5:2012 May 11 14:01:58:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 14:01:58:BMC:kernel:--<7>[peci_init_hardware]:472:peci:
registered IRQ: [13]
5:2012 May 11 14:01:58:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]:
630:BIOS_POST_CMPLT De-asserted --> BIOS is running
7:2012 May 11 14:01:58:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 14:01:58:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0000 files.
5:2012 May 11 14:01:59:BMC:IPMI:587: Pilot2SrvPower.c:394:
Blade Power Changed To: [ ON ]
5:2012 May 11 14:01:59:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:
2063:block_transfer_fetch_host_request_for_app: BT_OPEN:
HostDescriptor = 155 : Filename = BiosTech_1.txt
5:2012 May 11 14:01:59:BMC:BIOSReader:391: BIOSReader.c:227:File Open :
BiosTech_1.txt
5:2012 May 11 14:01:59:BMC:kernel:--<5>LPC Reset ISR -> ResetState: 1
7:2012 May 11 14:01:59:BMC:kernel:--<7>[peci_init_hardware]:490:peci:
unregistered IRQ: [13]
7:2012 May 11 14:01:59:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
1141:block_transfer_deallocate_entire_list
7:2012 May 11 14:01:59:BMC:kernel:--<7>[block_transfer_deallocate_entire_list]:
1185:block_transfer_deallocate_entire_list : Dumped: 0x0001 files.
```

```
5:2012 May 11 14:01:59:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:
  2125:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
  HostBTDescr = 155 : FName = BiosTech_1.txt
5:2012 May 11 14:01:59:BMC:BIOSReader:391: BIOSReader.c:555:File Close :
  /var/nuova/BIOS/BiosTech_1.txt
5:2012 May 11 14:01:59:BMC:kernel:-:<5>LPC Reset ISR -> ResetState: 0
7:2012 May 11 14:01:59:BMC:kernel:-:<7>[peci_init_hardware]:472:peci:
  registered IRQ: [13]
5:2012 May 11 14:01:59:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]:
  630:BIOS_POST_CMPLT De-asserted --> BIOS is running
7:2012 May 11 14:01:59:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
  1141:block_transfer_deallocate_entire_list
7:2012 May 11 14:01:59:BMC:kernel:-:<7>[block_transfer_deallocate_entire_list]:
  1185:block_transfer_deallocate_entire_list : Dumped: 0x0000 files.
6:2012 May 11 14:01:59:BMC:avct_server:-: Clear RVAS regs
5:2012 May 11 14:01:59:BMC:IPMI:591: VirtualSEL.c:224:SEL Evt[36 00]<
  36 00 02 D7 1B AD 4F 20 00 04 25 52 08 01 FF FF >
6:2012 May 11 14:02:00:BMC:avct_server:-: Set TSTMUL reg to 0x00100000
5:2012 May 11 14:02:00:BMC:IPMI:591: VirtualSEL.c:224:SEL Evt[37 00]<
  37 00 02 D8 1B AD 4F 20 00 04 25 53 08 00 FF FF >
6:2012 May 11 14:02:00:BMC:avct_server:-: Detected VGA Text Mode: 80 x 25 chars
6:2012 May 11 14:02:00:BMC:avct_server:-: Current Graphics Core Settings are:
6:2012 May 11 14:02:00:BMC:avct_server:-: 720 x 400, 4 bits per pixel, 640 pitch,
  in VGA mode
6:2012 May 11 14:02:00:BMC:avct_server:-: Video Signal detected: 720 x 400,
  color depth is: 4 bits
6:2012 May 11 14:02:00:BMC:avct_server:-: VGA Text mode
6:2012 May 11 14:02:00:BMC:avct_server:-: Change Detected before TFE start
5:2012 May 11 14:02:00:BMC:bioscom:-: lv_mode_dimm_support.c:126:
  [lpc_reset_seen]LPC Reset Count is Different [0x31:0x32]
  Asserted LPC Reset Seen
```