

# 如何在Cisco ESA、WSA和SMA上安装功能键？

## Contents

[Introduction](#)

[如何在Cisco ESA、WSA和SMA上安装功能键？](#)

[在CLI上安装功能键](#)

[在GUI上安装功能键](#)

[成功的安装](#)

[不成功的安装](#)

## Introduction

本文描述关于怎样的进程在物理Cisco电子邮件安全工具(ESA)，Web安全工具(WSA)和安全管理工具(SMA)上安装功能键。

## 如何在Cisco ESA、WSA和SMA上安装功能键？

功能键从do-not-reply@cisco.com被发送到功能键购买或续订的被提名的电子邮件地址。电子邮件包含一个附件用功能键可适用对购买或续订。

功能键的输出示例:在附件：

```
Serial Number : XXXXXXXXXXXX-AAAAAAAAAA
```

```
Type: Sophos Anti-Virus, apply by: <year>/<month>/<date>, expires: <year>/<month>/<date>  
Key : xxxxxx-aaaaa-bbbbbb-cccc--ddddd-xxxxx-aaaaa-bbbbbb-cccc--ddddd-fffff-eeee
```

```
Type: Webroot, apply by: <year>/<month>/<date>, expires: <year>/<month>/<date>  
Key : xxxxxx-aaaaa-bbbbbb-cccc--ddddd-xxxxx-aaaaa-bbbbbb-cccc--ddddd-fffff-eeee
```

```
Type: IronPort Web Reputation Filters, apply by: <year>/<month>/<date>,  
expires: <year>/<month>/<date>  
Key : xxxxxx-aaaaa-bbbbbb-cccc--ddddd-xxxxx-aaaaa-bbbbbb-cccc--ddddd-fffff-eeee
```

## 在CLI上安装功能键

```
CLI> featurekey
```

```
Enter feature key, or press Enter to go to the main prompt.
```

```
[ ]> <feature key - from the example above copy and paste the "key" section>
```

## 在GUI上安装功能键

1. 连接到**系统管理>功能键**。
2. 粘贴在**功能启动部分**的**键关于功能键**：字段。
3. 如镜像所显示，点击**SUBMIT**键。

Reporting Web Security Manager Security Services Network System Administration

Policy Trace  
Alerts  
Log Subscriptions  
Return Addresses  
SSL Configuration  
Users  
Network Access  
System Time  
Time Zone  
Time Settings  
Configuration  
Configuration Summary  
Configuration File  
Feature Key Settings  
Feature Keys  
Upgrade and Updates  
Upgrade and Update Settings  
System Upgrade  
System Setup  
System Setup Wizard  
FIPS Mode  
Next Steps

### Feature Keys

Feature Keys for Serial Number: 423F4E7150C767600ADB-2806218F46F3

Description	Status	Time Remaining
Cisco L4 Traffic Monitor	Active	317 days
Cisco HTTPS Proxy	Active	317 days
File Reputation	Active	73 days
Cisco Web Usage Controls	Active	317 days
Sophos	Active	317 days
File Analysis	Active	73 days
Webroot	Active	317 days
Cisco Web Proxy & DVS Engine	Active	317 days
Cisco AnyConnect Secure Mobility	Dormant	317 days
Cisco Web Reputation Filters	Active	317 days

**Pending Activation**

No feature key activations are pending.

**Feature Activation**

Feature Key:

## 成功的安装

- 提交许可证协议页。查看协议并且**接受**。
- 在协议被接受后，如镜像所显示，功能键安装提供的输出。

## Feature Keys

Success — Feature key accepted for host

Automatically checking for additional updates.  
No new feature keys are available.

## 不成功的安装

- 错误信息生成。如镜像所显示，消息为不成功的安装提供原因。  
(示例：“功能键是畸形的”或“功能键在主机已经使用了”)

### Feature Keys

**Error** — Errors have occurred. Please see below for details.

Feature Keys for Serial Number: 423F4E7150C767600ADB-280621BF46F3			
Description	Status	Time Remaining	Expiration Date
Cisco L4 Traffic Monitor	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco HTTPS Proxy	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco Web Usage Controls	Dormant	227 days	Sat Dec 10 13:59:59 2016
Sophos	Dormant	227 days	Sat Dec 10 13:59:59 2016
Webroot	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco Web Proxy & DVS Engine	Active	227 days	Sun Dec 11 11:29:20 2016
Cisco AnyConnect Secure Mobility	Dormant	227 days	Sat Dec 10 13:59:59 2016
Cisco Web Reputation Filters	Dormant	227 days	Sat Dec 10 13:59:59 2016

Note: The Cloud Web Security authorization key (or license key) is separate from the appliance feature keys. See Network > Cloud Connector to enter the authorization key.

**Pending Activation**

No feature key activations are pending.

[Check for New Keys](#)

**Feature Activation**

Feature Key:

Feature key is malformed.

[Submit Key](#)

**Note:** 推荐与Cisco准许的小组联系在licensing@cisco.com或开进一步协助的[支持案件](#)。